

Setup Guide

Q2-2008



Index and Cross Reference

Contents: **All new Additions or Changes are in RED.**

Cover Page

Index & Cross Reference

i 1-5

The Setup Pages

1-52

Warranty Conditions Sennheiser USA

Appendix A

RMA Form

Appendix B

Telephone Company / Manufacturer

3Com

Aastra Technologies

Aastra Intecom (Also see Intecom)

Acoustical Innovations

ACS Wireless (Also see GN Netcom)

Aegis Technologies

Alcatel (Also see Cortelco)

Allen Tel Products, Inc.

Allworx

Alston Tascom

Altigen Communications

American GST

American Phone Products

American Telecommunications

Ameriphone (See Carity a Division of Plantronics)

Amtelco

Anaconda Ericsson (See Ericsson Information Systems)

Aspect Telecommunications (Acquired by Concerto Software, Inc.)

Asuzi LTD.

AT&T (Also see Avaya)

Augat Melco

Audiovox

Automatic-Electric (See GTE)

Avaya (Also see AT&T and Lucent Technologies.

AvTec

Axon Communications

Bang & Olufsen America

BBS Telecom

Bellsouth Advanced Systems

Bitronics

Bizfon

Brother

British Telecom

CadCom TeleSystems

Centurion Inc.

CDT / Colonial Data Services Corp (No longer in Business)

Cidco

Cisco Systems

Clarity (Division of Plantronics)

Telephone Company / Manufacturer

CMX Communications
Code-A-Phone
Comcentrex
Comdial
Comfort Telecommunications
Conair Corporation
Console Systems
Contel Executone (See Executone GE Information Systems)
Contel IPC (See IPC Information Systems)
Conveyant Systems
Cortelco
CXC
Cyber Digital
Cybiotronics, LTD.
Cynet Technologies
DAK
Dasan Electron
Dash (See Picazo)
Data Plus
Data Point (See Teknekron Infoswitch Corp.)
Datavox
David Systems
Davox
DBA Telecom
DEC
Deka
Delos
Digital
Digital Systems Inc. (See Avaya, Merger)
DND Teletronics
Dong Jun
DSI (Digital Systems, Inc.) (See Avaya, Merger)
DTI / Digital Technics, Inc.
Danascan
Entel
eOn
Ericsson Info Systems
ESI (Estech Systems)
e-tel Corporation (See QTelNet, Merger)
Executone Information Systems
Extrom
Fujitsu Business Systems
GE General Electric
GN Netcom
GST America
GTE
Harris Digital Corporation
Hello Direct
Hewlett Packard (HP)
Hitachi

Telephone Company / Manufacturer

IBM
Innovative Communications
InSciTek (See Allworx)
Intecom (Acquired by Aastra Technologies)
Integrated Technology
Integrated Wave Technology
Interactive, Inc.
Interactive Intelligence, Inc.
Inter-Tel
I.P.C. Information Systems
ISDN*TEK
Isoetec (Bought out by Executone. Still has Isoetec name on product.)
ITT (See Cortelco)
Iwatsu America, Inc.
Kanda
Key Systems, U.S.
Lenoxx
Lexar (Also see Memorex Telex, or Telenova)
Linksys (Division of Cisco Systems)
Lucent Technologies (Also see Avaya and AT&T)
MacroTel
Marubeni America Corporation (See Nitsuko)
Mitel Networks
Modular Communication Systems
Motorola
Multilink, Inc.
Mura (See CDT Colonial Data Services Corp)
Murata
National Telecom / Solid State Systems
Natural MicroSystems
NEC America, Inc.
Newtronix Communications
Nitsuko America Corp.
Norstan
Nortel Networks (Also see Aastra Technologies)
Northern Telecom (See Nortel Networks)
Northcom
Northwestern Bell
Ontario Systems
Orbacom Systems
Page Industries
plamOne
Panasonic
Phone Mate Corporation
Picazo (Purchased by Intel)
Plant CML
Plant Equipment (See Plant CML)
Plantronics (Also see Ameriphone and Clarity)
Polycom
Positron

Telephone Company / Manufacturer

Premier Telecom Products, Inc. (Also see Sprint Products Group, Inc.)
Prostar Telecom
QTelNet
Radio Shack
RCA
Redcom Laboratories
Rockwell-Collins (See Rockwell FirstPoint Contact)
Rockwell International (See Rockwell FirstPoint Contact)
Rockwell FirstPoint Contact (Acquired by Concerto Software, Inc.)
Rolm (See Siemens Communications)
Samsung Telecommunications Systems
Sanyo Business Systems
SBC
Scitec
SDX Business Systems
Shared Resources Exchange (See Teltronics)
Sharp Electronics
Snom Technology
ShoreTel
Siemens Communications
Sipura Technology (See Linksys)
Smith Corona (See Comfort Telecommunications)
Solid State Systems
Solitaire Telecommunications
Sony
Southwestern Bell (See SBC)
Sprint Products Group, Inc. (Also see Premier Telecom Products, Inc.)
SRX (See Teltronics)
Startel
Sun Moon Star Group
Tadiran
TalTek
Tascom (See Alston Tascom)
TCO / Alcatel
Teknekron Infoswitch Corporation
Telamon-Tecom
Teleco
Telecom Technology
Telecom USA
TeleConcepts
Teleconnect (Also see Telecom USA)
Teledex
Teledial
Teledirect
Telefony and Electronics
Telematrix (Also see TeleConcepts)
Teloquent Communications
Telrad
TelStrat
Teltone

Telephone Company / Manufacturer	
Teltronics	
TIE Communicaitons	
Tone Commander Systems, Inc.	
Toshiba	
TT Systems	
Turret Equipment Corp.	
Uniden	
USB Recorder	
USX Telecenters	
V-Band Systems	
Vertical Networks	
VCON	
Vodavi Communications	
VTech	
VXI	
Walker (See Clarity a Division of Plantronics)	
WIN Communications	
Xinex Networks	
Zetron	

Manufacturer Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
3-COM				3-COM
NBX 100 Business Telephone	A-3/4	A-3/4	CSTD 24	2
NBX 1102 (3C10121), (3C10122)	A-3/4	A-3/4	CSTD 24	2
NBX 1102B (3C10281B)	A-3/4	A-3/4	CSTD 24	2
NBX 1102PE (3C10281PE)	A-3/4	A-3/4	CSTD 24	2
NBX 2101B (3C10248B)	A-3/4	A-3/4	CSTD 24	2
NBX 2101PE (3C10248PE)	A-3/4	A-3/4	CSTD 24	2
NBX 2102 (3C10226A)	A-3/4	A-3/4	CSTD 24	2
NBX 2102B (3C10226B)	A-3/4	A-3/4	CSTD 24	2
NBC 2102PE (3C10226PE)	A-3/4	A-3/4	CSTD 24	2
NBX 2102-IR (3C10228IRA)	A-3/4	A-3/4	CSTD 24	2
NBX 2102B-IR (3C10228IRB)	A-3/4	A-3/4	CSTD 24	2
NBX 2102PE-IR (3C10228IRPE)	A-3/4	A-3/4	CSTD 24	2
Entry Phone 3000 (3C10399A)	A-3/4	A-3/4	CSTD 01	2
Basic Phone 3101 (3C10401A)	A-3/4	A-3/4	CSTD 01	2
Basic Speaker Phone 3101 (3C10401SPKRA)	A-3/4	A-3/4	CSTD 01	2
Business Phone NBX 3102 (3C10402A)	A-3/4	A-3/4	CSTD 01	1
Manager Phone NBX 3103 (3C10403A)	A-3/4	A-3/4	CSTD 01	1
Cordless Sets:				
3106 (3C10406A), 3107 (3C10407A)	NO	NO	CCEL 190-2	3
<ol style="list-style-type: none"> 1. Connect to dedicated modular headset jack. 2. For Direct-Connect in the handset jack order the UI 710 for handset use. 3. Has 2.5 mm headset jack. Use the CCEL 190-2 cable. 				
Aastra Technologies				Aastra Technologies
CM-16 Wireless Phone	NO	NO	CCEL 190-2	3
Enterprise IP Phones:				
480i, 480i CT, 9133i, 9112i	A-3/4	A-3/4	CSTD 01	1
Meridian Sets:				
5008, 5208, 5316, 6310	A-3/4	A-3/4	CSTD 01	4
5216, 6320	A-3/4	A-3/4	CSTD 01	1
Business Sets:				
8004, 8009, 8314, 8417	A-3/4	A-3/4	CSTD 01	4
9009, 9110, 9116, 9216, 9316	A-3/4	A-3/4	CSTD 01	4
9120, 9417CW	A-3/4	A-3/4	CSTD 01	2,4
Maestro 1500 CW, 3500 CW	A-3/4	A-3/4	CSTD 01	4
Venture	A-3/4	A-3/4	CSTD 01	4
Vista / PowerTouch 150	A-3/4	A-3/4	CSTD 01	4
Vista / PowerTouch Screenphone 390, 392	A-3/4	A-3/4	CSTD 01	4
Vista / PowerTouch Screenphone 470	A-3/4	A-3/4	CSTD 01	4,7
Vista / PowerTouch Screenphone 480, 480H	A-3/4	A-3/4	CSTD 01	4,6
Vista / PowerTouch Screenphone 480e	A-3/4	A-3/4	CSTD 01	5
<ol style="list-style-type: none"> 1. Connect to dedicated modular headset jack. 2. Headset compatible. 3. Has 2.5 mm headset jack. Use the CCEL 190-2 cable. 4. For Direct-Connect in the handset jack order the UI 710 for handset use. 5. Has dedicated modular headset Jack and 2.5 mm headset jack. Use CCEL 190-2 for the 2.5 mm headset jack. 6. Has 3.5 mm headset jack. Use the CCEL 193 cable or the CCEL 190-2 with a 2.5 mm to 3.5 mm adapter. The headset switch next to the headset jack needs to be in the "ON" position for headset use. The handset will not work when the headset switch is in the "ON" position. 				

Manufacturer			Manufacturer		
Appliance / Telephone / Terminal		BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Aastra Continued			Aastra Continued		
7. Has 2.5 mm headset jack. Use the CCEL 190-2 cable. Phone "Options" program needs to be set for headset use.					
Acoustical Innovations			Acoustical Innovations		
GA-100 Multi-Purpose	NO	NO	CSTD 01		
Single-line headset phones:					
DP-8 with dial pad	NO	NO	CSTD 01		
TS-1 without dial pad	NO	NO	CSTD 01		
ACS Wireless			ACS Wireless		
Applica, AT II	NO	NO	CSTD 07		
Colleague, ISDN/DMS, MM II	NO	NO	CSTD 07		
Tri-Amp	NO	NO	CSTD 07		
RNA "Rep. Not Available" Amplifiers:					
OSD2, QD2, RD2	NO	NO	CSTD 07		
SSA	NO	NO	CSTD 01		
Aegis Technologies			Aegis Technologies		
Aegis Flex 200	A-3/4	A-3/4	CSTD 01	1	
1. For Direct-Connect in the handset jack order the UI 710 for handset use.					
Alcatel			Alcatel		
Alcatel 9 Series TDM Phones:					
4019, 4029	A-3/4	A-3/4	CSTD 01	2	
4039	A-3/4	A-3/4	CSTD 01	3	
IP Touch Phones:					
4018	A-3/4	A-3/4	CSTD 01	2	
4028, 4038	A-3/4	A-3/4	CSTD 01	3	
4068	A-3/4	A-3/4	CSTD 01	3,4	
Reflexes Sets:					
4004, 4010, 4020	A-3/4	A-3/4	CSTD 01	1,2	
4022 IP, 4037 IP	A-3/4	A-3/4	CSTD 01	1,2	
4035 Attendant Station	A-3/4	A-3/4	CSTD 01	1,2	
4059 Multimedia Attendant Station	A-3/4	A-3/4	CSTD 01	1,2	
1. Headset compatible.					
2. For Direct-Connect in the handset jack order the UI 710 for handset use.					
3. Connect to dedicated modular headset jack.					
4. Bluetooth enabled for use with wireless Bluetooth headset.					
Allen Tel Products, Inc.			Allen Tel Products, Inc.		
10 / 20 / D21230 Line Panel Set	A-8/9	A-8/9	NO	1	
GB10716PB Series	A-8/9	A-8/9	NO	1	
1. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.					
Allworx			Allworx		
Allworx 9102, 9112	NO	NO	CCEL 190-2	1,2	
IP 9202	A-3/4	A-3/4	CSTD 01	2	
IP 9212	A-3/4	A-3/4	CSTD 01	3	
1. Has 2.5 mm headset jack. Use the CCEL 190-2 cable.					
2. For Direct-Connect in the handset jack order the UI 710 for handset use.					
3. Connect to dedicated modular headset jack.					
Alston Tascom			Alston Tascom		
Tascom Legacy Console	A-8/9	A-8/9	CSHS 01	1,3	
Tascom SQL Digital PC Console	A-8/9	A-8/9	CSHS 01	1, 2,3	
1. May need modular to PJ 327 dual plug prong adapter SC-W478.					

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Alston Tascom Continued			Alston Tascom Continued	
2. The Digital PC Console can be ordered with Electret Modular. Use one of the following: <ul style="list-style-type: none"> A. UI 740, setting A-3/4 B. Direct Connect, CSTD 01 3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Altigen Communications			Altigen Communications	
AltiTouch Visualink Screenphone	A-5	A-5	CHS 01	1
AltiTouch Plus Visualink Screenphone	A-5	A-5	CHS 01	1
AltiTouch PT 390	A-5	A-5	CHS 01	1
AltiTouch 500, 510	A-3/4	A-3/4	CSTD 01	2
Alti-IP 600H, Alti-IP 600HP	A-3/4	A-3/4	CSTD 01	2
IP 705	A-3/4	A-3/4	CSTD 01	2
IP 710	A-3/4	A-3/4	CSTD 01	3
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. Connect to dedicated modular headset jack. 3. Has dedicated modular headset Jack and 2.5 mm headset jack. Use CCEL 190-2 for the 2.5 mm headset jack.				
American GST			American GST	
Premier 2500	A-8/9	A-8/9	NO	2
Starplus 616	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
American Phone Products			American Phone Products	
RC3000, XL30	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
American Telecommunications			American Telecommunications	
7010, 7016, 7102, 7110, 7116	A-3/4	A-3/4	CSTD 01	1
ATC Series Sets:				
100, 101, 110, 111, 200	A-3/4	A-3/4	CSTD 01	1
EZ Comm AT200-CG	A-3/4	A-3/4	CSTD 01	1
EZ Comm AT206	A-8/9	A-8/9	CSHS 01	1,2
Identity ATC1D	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Amtelco			Amtelco	
EVE: Infinity	A-8/9	A-8/9	CSHS 01	1,2
EVE: Operator Station	A-8/9	A-8/9	CSHS 01	1,2
EVE: PCMX	A-8/9	A-8/9	CSHS 01	1,2
1. Needs modular to PJ 327 dual plug prong adapter SC-W478. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Aspect Communications			Aspect Communications	
TeleSet 6050, 6190	A-8/9	A-8/9	CSHS 01	1,2
Digital TeleSets: 3010, 3190, 3192	A-8/9	A-8/9	CSHS 01	2
WinSet (CTI / IP)	A-8/9	A-8/9	CSHS 01	2
T3 IP Set	A-3/4	A-3/4	CSTD 01	3
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 3. Connect to dedicated modular headset jack.				

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Asuzi LTD.			Asuzi LTD.	
Pro 616, 1032 Sets	A-8/9	A-8/9	CSHS 01	1,2
Pro XL 616, 1032 Sets	A-3/4	A-3/4	CSTD 01	1
SDX Sets FT-1, -2, -3, -4	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
AT&T			AT&T	
915, 927, 952, 954, 957	NO	NO	CSTD 01	2
958-R, 959, 962, 1545, 1818, 1872	NO	NO	CSTD 01	2
924, 944, 944-R, 945, 952, 955	NO	NO	CSTD 01	1,2
955-R, 964, 964-R, 972, 974, 982, 984	NO	NO	CSTD 01	1,2
992, 1855	NO	NO	CSTD 01	1,2
Cordless Sets: 1412, 2231, 2300, 2402, 2462	NO	NO	CCEL 190-2	1
E580-1, E580-2, E2115, E2125	NO	NO	CCEL 190-2	1
E250, E252, E2525	NO	NO	CCEL 190-2	1
E2555, E2562, E2600B, E2725B	NO	NO	CCEL 190-2	1
E5860, E5865, E5925B, E5965C	NO	NO	CCEL 190-2	1
EP5962	NO	NO	CCEL 190-2	1
Trimline 210	See Note	See Note		3
1. Has 2.5 mm headset jack. Use the CCEL 190-2 cable.				
2. For Direct-Connect in the handset jack order the UI 710 for handset use.				
3. Has dial (Touchtone Pad) in handset. Headsets are not compatible.				
Augat Melco			Augat Melco	
MAX-128, -424, -824 Console	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Audiovox			Audiovox	
Analog Wireless Series:				
CTX3600, CTX3600A	See Note	See Note		1
PRT9100, PRT9200	See Note	See Note		1
CDMA Wireless Series:				
CDM8450BM, CDM8450SP, CDM8455WWE	NO	NO	CCEL 190-2	
CDM8500, CDM8600, CDM8600BA	NO	NO	CCEL 190-2	
CDM8600BM, CDM8610VM, CDM8615BM	NO	NO	CCEL 190-2	
CDM8615CS, CDM8615M, CDM8615M	NO	NO	CCEL 190-2	
CDM8615MW, CDM8900, CDM8900M	NO	NO	CCEL 190-2	
CDM8900T, CDM8900US, CDM8900VW	NO	NO	CCEL 190-2	
CDM8900WW, CDM8910AL, CDM8910BM	NO	NO	CCEL 190-2	
CDM8910C, CDM8910CS, CDM8910NT	NO	NO	CCEL 190-2	
CDM8910US, CDM8910VM, CDM8910WW	NO	NO	CCEL 190-2	
CDM8940VW, CDM9900VW, CDM9950SP	NO	NO	CCEL 190-2	
PM8912, PM8920KIT	NO	NO	CCEL 190-2	
GSM Wireless Series:				
GDU325, GDU325XL, GDX250	NO	NO	CCEL 190-2	
GDX250XL, GDX300, GDX300XL	NO	NO	CCEL 190-2	
GDX325, GDX325XL, GDX350	NO	NO	CCEL 190-2	
GDX350XL, GSM810	NO	NO	CCEL 190-2	
SMT5600, TM150	NO	NO	CCEL 190-2	
WP718	NO	NO	CCEL 190-2	
PCS Wireless Series:				

Manufacturer		Manufacturer			
Appliance / Telephone / Terminal		BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Audiovox Continued		Audiovox Continued			
PCX1000XL, PCX1000XLE, PCX1000XLGTE		See Note	See Note		1
PCX1000XLP, PCX1000XLUSU		See Note	See Note		1
PCX1100XL, PCX1110XL		See Note	See Note		1
TDMA Wireless Series:					
T300, TDM2500, TDM2500XL		NO	NO	CCEL 190-2	
Cordless Telephone Sets:					
DST961, DT911, DT921C, DT941CI		See Note	See Note		1
DT931C, DT951CI, GX2400		NO	NO	CCEL 190-2	
GX2401C, GX2411CI, TL1000		NO	NO	CCEL 190-2	
TL1100, TL1102, TL1200A		NO	NO	CCEL 190-2	
1. These wireless sets do not have a headset jack.					
Avaya		Avaya			
100, 110, 130, 135, 140, 145		A-3/4	A-3/4	CSTD 01	7
1510, 1511, 1516, 1521, 1523		A-3/4	A-3/4	CSTD 01	7
1525, 1527, 1531, 1532, 1545		A-3/4	A-3/4	CSTD 01	7
1600, 1845, 1854, 1872, 4293		A-3/4	A-3/4	CSTD 01	7
2402 Digital Telephone		A-5/6	A-5/6	CHS 01	7
2410, 2420 Digital Telephone		A-5/6	A-5/6	CHS 01	5
2500 Sets with Carbon Mic:					
DMGC, DMGF, DMGH		A-8/9	A-8/9	CHSH 01	7,8
M, MM, MMG, MMGB		A-8/9	A-8/9	CHSH 01	7,8
MMGL, SM, YMGM		A-8/9	A-8/9	CHSH 01	7,8
2500 Sets with Electret Mic:					
DMGJ, DMGK, DMGL		A-3/4	A-3/4	CSTD 01	7
MMGJ, MMGK, MMGT		A-3/4	A-3/4	CSTD 01	7
YMGD, YMGJ, YMGK, YMGL		A-3/4	A-3/4	CSTD 01	7
2511, 2514, 2515, 2554, 2558, 2563		A-8/9	A-8/9	CHSH 01	7,8
2564, 2565, 2568, 2575, 2630, 2631		A-8/9	A-8/9	CHSH 01	7,8
2634, 2635, 2636, 2637, 2660, 2662		A-8/9	A-8/9	CHSH 01	7,8
2702, 2830, 2831, 2836, 2837, 2851		A-8/9	A-8/9	CHSH 01	7,8
2991, 2992, 2993, 2994		A-8/9	A-8/9	CHSH 01	7,8
400, 410, 412, 420, 422, 460		A-3/4	A-3/4	CSTD 01	7
4295, 4297, 4298, 4299		A-3/4	A-3/4	CSTD 01	7
480, 600, 610, 612, 620, 622		A-3/4	A-3/4	CSTD 01	7
4600 IP Series Sets:					
4601 IP, 4602 IP Telephone		A-3/4	A-3/4	CSTD 01	7
4606 IP, 4610 IP, 4612 IP, 4624 IP		A-3/4	A-3/4	CSTD 01	4
4620 IP, 4630 Screenphone, IP Softphone		A-3/4	A-3/4	CSTD 01	4
New 4600 IP Series Sets:					
4610SW, 4620SW, 4621SW		A-3/4	A-3/4	CSTD 01	4
4622SW, 4625SW, 4630SW		A-3/4	A-3/4	CSTD 01	4
500, 558, 564, 465, 568, 575		A-8/9	A-8/9	CHSH 01	7,8
585, 630, 631, 635, 662, 830		A-8/9	A-8/9	CHSH 01	7,8
5400 Series IP Office Phones					
5402		A-5	A-5	CHS 01	7
5410, 5420		A-5	A-5	CHS 01	5
5600 Series IP Office Phones					
5601, 5602		A-3/4	A-3/4	CSTD 01	7
5610, 5620		A-3/4	A-3/4	CSTD 01	5

Manufacturer	Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer	Notes
Avaya Continued		Avaya Continued				
	6210, 6211, 6218, 6219, 6220, 6221	A-3/4	A-3/4	CSTD 01		7
	6402, 6402D, 6408, 6408+	A-3/4	A-3/4	CSTD 01		7
	6408D+, 6414, 6416, 6416D	A-3/4	A-3/4	CSTD 01		7
	6416D+, 6424, 6424D, 6424D+	A-3/4	A-3/4	CSTD 01		7
	6410 D+M, 6416 D+M, 6424 D+M	A-3/4	A-3/4	CSTD 01		5
	6514, 6516	A-3/4	A-3/4	CSTD 01		7
	700, 706, 710, 712, 715, 720	A-3/4	A-3/4	CSTD 01		7
	722, 725, 730, 732, 740, 742, 764	A-3/4	A-3/4	CSTD 01		7
	812, 815, 822, 824, 830	A-3/4	A-3/4	CSTD 01		7
	832, 842, 843, 853, 854, 864	A-3/4	A-3/4	CSTD 01		7
	831, 851, 852, 1662	A-8/9	A-8/9	CSHS 01		7,8
	8101, 8102, 8110	A-3/4	A-3/4	CSTD 01		3,7
	8400, 8403, 8405, 8406	A-3/4	A-3/4	CSTD 01		3,7
	8410, 8411, 8434	A-3/4	A-3/4	CSTD 01		3,7
	8503, 8510, 8520, 8528	A-3/4	A-3/4	CSTD 01		3,7
	880, 882, 906, 912, 922, 925	A-3/4	A-3/4	CSTD 01		7
	930, 932, 951, 954, 960, 965	A-3/4	A-3/4	CSTD 01		7
	970, 980, 1504, 1506, 1509	A-3/4	A-3/4	CSTD 01		7
	Attendant Consoles:					
	300A1-A, 301A1-A, 301B1-A, 302A	A-8/9	A-8/9	CSHS 01		1,8
	302C, 310-A1-03, 311A, 551, 557, 50B	A-8/9	A-8/9	CSHS 01		1,8
	302D	A-3/4	A-3/4	CSTD 01		1
	Call Master I (602)	A-8/9	A-8/9	NO		1,2
	Call Master II (603A1, 603D)	A-8/9	A-8/9	NO		1,2
	Call Master III (603E)	A-8/9	A-8/9	NO		1,2
	Call Master IV (603F, 603G)	A-8/9	A-8/9	CSHS 01		1,8
	Call Master V (607A1), VI (606A1)	C-3/4	C-3/4	CSTD 08		
	IP Wireless Telephones:					
	3616, 3626	NO	NO	CCEL 190-2		
	Merlin & 7000 Series Sets with "R" style handset. These are 1985-1990 vintage:					
	7101, 7104, 7302, 7309, 7434D	NO	NO	NO		
	7102, 7103, 7203, 7205, 7401	See Note	See Note			9
	7302, 7303, 7305					
	7402, 7403, 7404, 7405, 7406	See Note	See Note			9
	7407, 7408, 7410, 7434, 7444	See Note	See Note			9
	7501, 7505, 7506, 7507	See Note	See Note			9
	7514, 7515, 7516, 7526	See Note	See Note			9
	Merlin 5 Button Set HFA1-10	NO	NO	NO		
	Merlin 10 & 34 Button Sets	See Note	See Note			9
	Merlin BIS 10, 22, 34 Button Sets	See Note	See Note			9
	Merlin 7313, 7314, 7315	See Note	See Note			9
	Merlin 7316, 7317, 7318	See Note	See Note			9
	Merlin Legend MLX-5,	A-3/4	A-3/4	CSTD 01		7
	Merlin Legend MLX-10, 16, 20, 28	A-3/4	A-3/4	CSTD 01		7
	Definity / Merlin Magix Wireless					
	Headset Telephone: LKA10	See Note	See Note	CCEL 191		

Manufacturer Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
Avaya Continued				Avaya Continued
Merlin Magix 4400, 4400+	A-3/4	A-3/4	CSTD 01	7
Merlin Magix 4406 D+, 4412 D+	A-3/4	A-3/4	CSTD 01	5
Merlin Magix 4424 D+, 4424 LD+	A-3/4	A-3/4	CSTD 01	5
one-X Deskphones:				
1603, 1608, 1616 IP Telephones	A-3/4	A-3/4	CSTD 24	5
9620, 9630, 9640, 9650 IP Telephones	A-3/4	A-3/4	CSTD 24	5
Partner / Partner MLS Wireless				
Headset Telephone: 10U100	See Note	See Note	CCEL 191	
Partner 6, 12, 18, 18D, 34D	A-3/4	A-3/4	CSTD 01	7
Partner MLS 6, MLS 18	A-5	A-5	CHS 01	7
Partner MLS 12D, 18D, MLS 34D	A-5	A-5	CHS 01	7
Predictive Dialer Mosaic 5000, OLIC	A-3/4	A-3/4	CSTD 01	7
Predictive Dialer P-Dial	A-8/9	A-8/9	CSHS 01	7,8
Predictive Dialer Voice Link	A-8/9	A-8/9	CSHS 01	1,8
Spirit 6, 24 Button Sets	A-3/4	A-3/4	CSTD 01	8
TransTalk 9040 Wireless Handset	NO	NO	NO	6
AT&T / Avaya / Lucent Headset Adapters:				
500A, 500A1, 502A, 502C	A-8/9	A-8/9	NO	1,2
500AM	NO	NO	CSTD 08	5
8400 One-Touch Adapter (SOTA) # 65672-01	NO	NO	CSTD 08	
Partner One-Touch Adapter # 3276-090	NO	NO	CSTD 08	
<ol style="list-style-type: none"> Needs modular to PJ 327 dual plug prong adapter SC-W478. Does not have a Receive volume control. Use of the AIA 01 with CSTD 01 cable or UI 740 is recommended for Receive volume control. If headset adapter is used check compatibility of "AT&T / Avaya / Lucent Headset Adapters" listed above. Connect to dedicated modular headset jack. Phone must be programmed for headset use. Handset becomes monitor only at this point. Connect to dedicated modular headset jack. Has 3.5 mm headset jack with non-standard wiring. Not compatible. For Direct-Connect in the handset jack order the UI 710 for handset use. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. Compatible only if one of the "AT&T / Avaya / Lucent Headset Adapters" is used listed above. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it, Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 				
AvTec				AvTec
Access System Console	A-8/9	A-8/9	CSHS 01	1,2
Dispatch System Console	A-8/9	A-8/9	CSHS 01	1,2
Dispatch Work Station	A-8/9	A-8/9	CSHS 01	1,2
DSPatch32 Work Station	A-8/9	A-8/9	CSHS 01	1,2
<ol style="list-style-type: none"> Some Consoles may require a 6-wire dual plug prong amplifier. Use SC911-15A. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 				
Axon Communications				Axon Communications
Axon 4, 4V, 8000	A-8/9	A-8/9	CSHS 01	1,2
<ol style="list-style-type: none"> For Direct-Connect in the handset jack order the UI 710 for handset use. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 				

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal		BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable # Notes
Bang & Olufsen America			Bang & Olufsen America	
BeoCom 3 Teleset		NO	NO	CCEL 192 1
1. CCEL 192 (4-pole, 2.5 mm plug) is not a USA stock item. Special order only.				
BBS Telecom			BBS Telecom	
IPS Key Telephones: IVT16D, IVT16N		A-3/4	A-3/4	CSTD 01 1,2
Plexus Key Phone PVT-30, PVT-30D		A-3/4	A-3/4	CSTD 01 1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
2. Headset compatible.				
Bellsouth Advanced Systems			Bellsouth Advanced Systems	
232, 236, 310, 320, 350, 360, 370, 380		A-3/4	A-3/4	CSTD 01 1
470, 473, 480, 1200, 4300		A-3/4	A-3/4	CSTD 01 1
Supremacy : 221, 223, 227, 231		A-3/4	A-3/4	CSTD 01 1
System 30 / Cascade 30, 2000 Set		A-3/4	A-3/4	CSTD 01 1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Bitronics			Bitronics	
308 Thrifty Station Set		See Note	See Note	See Note 1
Bitronic 4 Button, 8 Button, 16 Button		See Note	See Note	See Note 1
Data Com 816, 2464		See Note	See Note	See Note 1
HyMax Station Set		See Note	See Note	See Note 1
KeySet, Display Set, EZPhone		See Note	See Note	See Note 1
1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.				
Bizfon, Inc.			Bizfon, Inc.	
BizTouch 2		A-3/4	A-3/4	CSTD 01 2
BizTouch 3		A-3/4	A-3/4	CSTD 01 1
1. Connect to dedicated modular headset jack.				
2. For Direct-Connect in the handset jack order the UI 710 for handset use.				
British Telecom			British Telecom	
Traders Turret: ITS BV405		A-8/9	A-8/9	CSHS 01 1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Brother			Brother	
FAX275, FAX565, FAX775, FAX1820C		A-3/4	A-3/4	CSTD 01 1
Inkjet Fax 1820C		A-3/4	A-3/4	CSTD 01 1
Intella Fax 620, 725, 770		A-3/4	A-3/4	CSTD 01 1
Interfax 780 MC, 1550 MC, 1970 MC		A-3/4	A-3/4	CSTD 01 1
Laser Fax PPF-2800, PPF-4100		A-3/4	A-3/4	CSTD 01 1
Telefax 675, 680		A-3/4	A-3/4	CSTD 01 1
Thermal Fax FAX-275, PPF-775		A-3/4	A-3/4	CSTD 01 1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
CadCom Telesystems			CadCom Telesystems	
DBX Console: 1200, 3420, 5000		A-8/9	A-8/9	CSHS 01 1,2,3
Legend Console: 3600		A-8/9	A-8/9	CSHS 01 1,2,3
Line Master Console: 3020, 3420		A-8/9	A-8/9	CSHS 01 1,2,3
1. May need modular to PJ 327 dual plug prong adapter SC-W478.				
2. For Direct-Connect in the handset jack order the UI 710 for handset use.				
3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Centurion			Centurion	
Cares Interface		NO	NO	CEDPC 1

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
CDT / Colonial Data Services			CDT / Colonial Data Services	
AP1000, AP2000, AP2001	See Note	See Note	See Note	1
AP2002, AP3002	See Note	See Note	See Note	1
1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.				
Cidco Communications Corp.			Cidco Communications Corp.	
Corded Telephones:				
CT15, CT17, CT200, CT250, CST2100	A-3/4	A-3/4	CSTD 01	2
Cordless Telephone Sets:				
CL906, CL910, CL915, CL930	NO	NO	CCEL 190-2	
CL990, CL991, CL992	NO	NO	CCEL 190-2	
D271, D933, D936	NO	NO	CCEL 190-2	
E2400, E9005, E9010, E9020	NO	NO	CCEL 190-2	
IP210CX	A-3/4	A-3/4	CSTD 01	1
1. Connect to dedicated modular headset jack.				
2. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Cisco Systems			Cisco Systems	
7900 Series IP Phones:				
7902G, 7905, 7905G, 7910G	A-3/4	A-3/4	CSTD 24	1
7910G-SW, 7911G, 7912G	A-3/4	A-3/4	CSTD 24	1
7920 Wireless IP Phone	NO	NO	CCEL 192	3
7940G, 7941G, 7960G, 7961G, 7970G	C-3/4	C-3/4	CSTD 08	2,4
7971G-GE, 7985G	C-3/4	C-3/4	CSTD 08	2,4
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
2. Connect to dedicated modular headset jack.				
3. CCEL 192 (4-pole, 2.5 mm plug) is not a USA stock item. Special order only.				
4. If connecting to the handset jack with a BW 900 or UI Box use setting A-3/4.				
Clarity			Clarity	
Ameriphone Telephones:				
Dialogue: JV-35, XL-25, XL-30	A-3/4	A-3/4	CSTD 01	2
Dialogue: XL-40, XL-50	A-3/4	A-3/4	CSTD 01	2
Ameriphone Wireless: CL-40, CLS45i	NO	NO	CCEL 190-2	
Clarity Telephones:				
C320, C510, W300	A-3/4	A-3/4	CSTD 01	1
W1000, W1100	A-3/4	A-3/4	CSTD 01	2
Clarity Wireless:				
C430, C435, C440, C600	NO	NO	CCEL 190-2	
W425	NO	NO	NO	
HA 40 Phone Receive Amplifier	NO	NO	CSTD 01	
MHA 100 Cordless phone Receive Amplifier	NO	NO	CCEL 190-2	1
1. Has 2.5 mm Headset Jack. Use the CCEL 190-2 cable.				
2. For Direct-Connect in the handset jack order the UI 710 for handset use.				
CMX Communications			CMX Communications	
Citation II, Citation Plus	See Note	See Note	See Note	1
Citation SST, Citation EST	See Note	See Note	See Note	1
1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.				

Manufacturer Appliance / Telephone / Terminal			BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
Code-A-Phone			Code-A-Phone			
1050, 1350, 1390, 1850, 1870	A-3/4	A-3/4	CSTD 01	1		
1950, 1990, 2050, 2150, 2350	A-3/4	A-3/4	CSTD 01	1		
2570, 2650, 2670, 2690, 3100	A-3/4	A-3/4	CSTD 01	1		
3200, 3350, 3390, 3450, 3490	A-3/4	A-3/4	CSTD 01	1		
3570, 4010, 4030, 4050, 4060	A-3/4	A-3/4	CSTD 01	1		
4080, 4150, 4250, 4275, 4290	A-3/4	A-3/4	CSTD 01	1		
4350, 4650, 5890, 6250, 6950	A-3/4	A-3/4	CSTD 01	1		
7050, 7150, 7410, 7420, 7425	A-3/4	A-3/4	CSTD 01	1		
7530, 7650, 8100, 8150, 8250	A-3/4	A-3/4	CSTD 01	1		
8410, 8415, 8420, 8425, 8440	A-3/4	A-3/4	CSTD 01	1		
Intrepid : 308, 516	A-3/4	A-3/4	CSTD 01	1		
1. For Direct-Connect in the handset jack order the UI 710 for handset use.						
Comcentrex			Comcentrex			
Centurion Console	A-8/9	A-8/9	CSHS 01	1,2,3		
1. Needs modular to PJ 327 dual plug prong adapter SC-W478.						
2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.						
3. Some Consoles may require a 6-wire dual plug prong amplifier. Use the SC911-15A.						
Comdial			Comdial			
1654, 1704, 1705, 1706, 1716	A-8/9	A-8/9	CSHS 24	4,5		
1800, 1810, 2500, 2502, 2503	A-8/9	A-8/9	CSHS 24	4,5		
2507, 2508, 2510, 2527, 2550	A-8/9	A-8/9	CSHS 24	4,5		
2551, 2552, 2553, 2554, 2556	A-8/9	A-8/9	CSHS 24	4,5		
2564, 2565, 2567, 2575, 2579	A-8/9	A-8/9	CSHS 24	4,5		
2800, 2805, 2806, 2810, 2816	A-8/9	A-8/9	CSHS 24	4,5		
2830, 2831, 2835, 2842, 2843	A-8/9	A-8/9	CSHS 24	4,5		
2844, 2851, 2854, 2860, 2861	A-8/9	A-8/9	CSHS 24	4,5		
2864, 2870, 3500, 3507, 3508	A-8/9	A-8/9	CSHS 24	4,5		
3506, 3514, 3609, 3679, 3709	A-3/4	A-3/4	CSTD 01	4		
3509, 3513, 3528, 3529, 3564	A-8/9	A-8/9	CSHS 24	4,5		
3525, 3527, 3567, 3579, 3625	A-8/9	A-8/9	CSHS 24	4,5		
3644, 3654	A-8/9	A-8/9	CSHS 24	4,5		
3779, 3879, 3889, 3979, 3989	A-3/4	A-3/4	CSTD 01	4		
DX 80 Digital Speakerphone 7260	A-3/4	A-3/4	CSTD 01	3,4		
DXP-TC-PKD	A-3/4	A-3/4	CSTD 01	2		
Executech I Sets:						
3500, 3502, 3503, 3508, 3593, 3598	A-3/4	A-3/4	CSTD 01	4		
3600, 3609, 3704, 3714, 3789, 3809	A-3/4	A-3/4	CSTD 01	4		
3810, 3878, 3889, 3910, 3979, 3989	A-3/4	A-3/4	CSTD 01	4		
4500, 4507, 4509, 4579, 4625, 4644	A-3/4	A-3/4	CSTD 01	4		
4706, 4709, 4719, 4779, 4789, 4879	A-3/4	A-3/4	CSTD 01	4		
4889, 4909, 4979, 4989	A-3/4	A-3/4	CSTD 01	4		
Executech II Sets:						
6600	A-3/4	A-3/4	CSTD 01	2		
6016, 6414, 6509, 6579, 6610, 6614	A-3/4	A-3/4	CSTD 01	4		
6620, 6622, 6700, 6701, 6702, 6706	A-3/4	A-3/4	CSTD 01	4		
6714, 6720, 6800, 6814, 6820	A-3/4	A-3/4	CSTD 01	4		
Impact Classic DSU Sets:						
8101N	A-3/4	A-3/4	CSTD 01	4		
8112N, 8112S, 8124S	A-3/4	A-3/4	CSTD 01	1,4		
8012S, 8024S	A-3/4	A-3/4	CSTD 01	2		

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Comdial Continued			Comdial Continued	
Impact SCS Sets:				
8201 Single Line Set	A-3/4	A-3/4	CSTD 01	4
8212S, 8312S, 8324S, 8412F	A-3/4	A-3/4	CSTD 01	2
Impact SCS iPrimo IP Phone: 8900-IP	A-3/4	A-3/4	CSTD 01	2
Impression Sets:				
2022, 2101, 2122	A-3/4	A-3/4	CSTD 01	4
Solo Sets:				
3522, 3523, 3582, 3583	A-3/4	A-3/4	CSTD 01	4
Solo II Sets:				
5300, 5400, 5500, 5521	A-3/4	A-3/4	CSTD 01	4
5531, 5631, 5641	A-3/4	A-3/4	CSTD 01	4
Unisyn Sets :				
1022S, 1122S, 1122X	A-3/4	A-3/4	CSTD 01	1,4
Voice Express: VX-41B, VX-41C	See Note	See Note	See Note	6
<ol style="list-style-type: none"> Headset compatible. Connect to dedicated modular headset jack. Has 2.5 mm headset jack. Use the CCEL190-2 cable. For Direct-Connect in the handset jack order the UI 710 for handset use. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 				
Comfort Telecommunications			Comfort Telecommunications	
Smith Corona and Comfort Tel Brand				
SC PD 100 (headset phone)	NO	NO	CSTD 01	
SC PD 200 (headset phone, no keypad)	NO	NO	CSTD 01	
SC M14 Multi-Purpose Amplifier	NO	NO	CSTD 01	
Conair Corporation			Conair Corporation	
Prima: PR1001, PR1006, PR2001	See Note	See Note		1
Prima: PR3001, PR6200, PR6221	See Note	See Note		1
SW2502, SW3502	See Note	See Note		1
TT201, TT2503	See Note	See Note		1
<ol style="list-style-type: none"> Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 				
Console Systems			Console Systems	
Centurion Console	A-8/9	A-8/9	CSHS 01	1,2,3
MicroCom Console	A-8/9	A-8/9	CSHS 01	1,2,3
MiniCom I, MiniCom II	A-8/9	A-8/9	CSHS 01	1,2,3
<ol style="list-style-type: none"> Needs modular to PJ 327 dual plug prong adapter SC-W478. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. Some Consoles may require a 6-wire dual plug prong amplifier. Use the SC911-15A. 				
Conveyant Systems			Conveyant Systems	
Centrex Console, TeleDesk	A-8/9	A-8/9	CSHS 01	1,2
<ol style="list-style-type: none"> For Direct-Connect in the handset jack order the UI 710 for handset use. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 				

Manufacturer Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
Cortelco				Cortelco
2500 44-20S-94S, 2500 44-VBA-20MC	A-8/9	A-8/9	CSHS 24	4,5
2500, 2502, 2544, 2554, 2564	A-8/9	A-8/9	CSHS 24	4,5
2565, 2566, 2567, 2842	A-8/9	A-8/9	CSHS 24	4,5
2843, 2844, 2854, 2861	A-8/9	A-8/9	CSHS 24	4,5
2870, 2871, 3554	A-8/9	A-8/9	CSHS 24	4,5
3100 XL Sets:				
Console: 237501 TLP, 237501 TSP	See Note	See Note		6
3100 XL 2630, 2672, 2673	See Note	See Note		6
3100 XL 281075, 281175, 281575	See Note	See Note		6
3100 XL 281975, 282075, 282175	See Note	See Note		6
3100 XL 2825, 2872, 2873	See Note	See Note		6
3100 XL 282575, 282975	See Note	See Note		6
4-Line Set: 412541-TP1-27S	A-3/4	A-3/4	CSTD 24	1,4
Alcatel 100	A-8/9	A-8/9	CSHS 24	5,7
Alcatel 901, 903, 904	See Note	See Note		6
Aries Digital Telephones:				
Basic Telephone, ADTB00-	A-3/4	A-3/4	CSTD 01	4
Standard Telephone, ADST00-	A-3/4	A-3/4	CSTD 01	4
Executive Telephone, ADTE00-	A-3/4	A-3/4	CSTD 01	4
Deluxe Telephone, ADTD00-	A-3/4	A-3/4	CSTD 01	4
Standard-Plus Telephone, ADTP00-	A-3/4	A-3/4	CSTD 01	4
Centurion Sets:				
369000VOE20F, 369044VOE20F	A-3/4	A-3/4	CSTD 01	4
369100VOE27F, 369144VOR27F	A-3/4	A-3/4	CSTD 01	4
369300VOE27S, 369344VOE27F	A-3/4	A-3/4	CSTD 01	4
Cordless Telephone Sets:				
5860, 5880	NO	NO	CCEL 190-2	
Transonic (730901-TP2-27F)	NO	NO	CCEL 190-2	
Citation Sets:				
2020, 2021, 2022, 2025	A-8/9	A-8/9	CSHS 24	4,5
Colleague Sets:				
2201, 2202	A-3/4	A-3/4	CSTD 01	4
2203, 2204, 2205	A-3/4	A-3/4	CSTD 01	1,4
Colleague Enhanced Sets:				
2200, 2210, 2211, 2220	A-3/4	A-3/4	CSTD 01	2,4
Compass Wireless PBX Handsets	NO	NO	CCEL 190-2	
ECS Set	See Note	See Note		6
EKS 616 Set	A-8/9	A-8/9	CSHS 24	4,5
EKS Console	A-3/4	A-3/4	CSTD 01	4
EKS CS 1024 Console	See Note	See Note		6
EKS 2701, 2801, 2802, 2803	A-8/9	A-8/9	CSHS 24	4,5
EKS 804, 2805, 2806	See Note	See Note		6
EzTouch 240085	A-3/4	A-3/4	CSTD 01	4
Feature Phone PC 1008	A-3/4	A-3/4	CSTD 01	4
Feature Phone 3480, 3482, 3484	A-3/4	A-3/4	CSTD 01	4
Feature Phone 3485, 3490, 3495	A-3/4	A-3/4	CSTD 01	4
Feature Phone 4525, 4535	A-3/4	A-3/4	CSTD 01	4
ISDN Set CI-1800 MOE-25D	A-3/4	A-3/4	CSTD 01	1,4
Margate (440585VOETLD)	A-3/4	A-3/4	CSTD 01	4
Medallion 2480, 2481, 2482, 2485	A-8/9	A-8/9	CSHS 24	4,5

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Cortelco Continued			Cortelco Continued	
Medallion Sets:				
3200 41TP227S, 3220 41TP227S	A-3/4	A-3/4	CSTD 01	3,4
Millennium 911800	A-3/4	A-3/4	CSTD 01	1,4
NKS 550, 900, 2900, 2930	A-8/9	A-8/9	CSHS 24	4,5
Patriot Sets:				
2190, 2191, 2192, 2194	A-3/4	A-3/4	CSTD 01	4
2193	A-3/4	A-3/4	CSTD 01	1,4
Select (371900TP227N & 371921TP227N)	A-3/4	A-3/4	CSTD 01	4
Sentry (879015TP227S)	A-3/4	A-3/4	CSTD 01	4
Tel-Trex 2980	A-3/4	A-3/4	CSTD 01	1,4
Tel-Trex II 3980, 3982, 3984, 3989	See Note	See Note		6
Tel-Trex II 3981, 3983, 3985	See Note	See Note		6
TP 100 Switchboard	A-8/9	A-8/9	CSHS 24	
Tribute 2010, 2011, 2012, 2015	A-8/9	A-8/9	CSHS 24	4
VoIP 2747 (274701-VIP-PAK)	A-3/4	A-3/4	CSTD 01	4
Voyage (200575VOE21F)	A-3/4	A-3/4	CSTD 01	4
<ol style="list-style-type: none"> 1. Turn headset switch on the bottom of the phone to the "ON" position for headset use. 2. Connect to dedicated modular headset Jack or 2.5 mm headset jack. Use CCEL 190-2 for the 2.5 mm headset jack. 3. Has 2.5 mm headset jack. Use the CCEL 190-2 cable. 4. For Direct-Connect in the handset jack order the UI 710 for handset use. 5. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 6. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 7. Needs modular to PJ 327 dual plug prong adapter SC-W478. 				
CXC			CXC	
Rose Series Sets:				
T1000, T2001, T2002, T2003	A-3/4	A-3/4	CSTD 01	1
T2004, T2005, T2064	A-3/4	A-3/4	CSTD 01	1
<ol style="list-style-type: none"> 1. For Direct-Connect in the handset jack order the UI 710 for handset use. 				
Cyber Digital			Cyber Digital	
Integrated Terminal IST-12, IST-20	A-8/9	A-8/9	CSHS 01	1,2
<ol style="list-style-type: none"> 1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 				
Cybiotronics, LTD.			Cybiotronics, LTD.	
CybioLink CY-2135	NO	NO	CCEL 190-2	
CybioLink P-I	NO	NO	CCEL 190-2	
CybioLink 8000	A-3/4	A-3/4	CSTD 01	1
CybioLink 8500	NO	NO	CCEL 190-2	
<ol style="list-style-type: none"> 1. For Direct-Connect in the handset jack order the UI 710 for handset use. 				
Cygnnet Technologies			Cygnnet Technologies	
CoSystem	A-8/9	A-8/9	CSHS 01	1,2
<ol style="list-style-type: none"> 1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 				

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
DAK			DAK	
4000 AX, 5000 IRX	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Dasan Electron			Dasan Electron	
DA-175 (Headset Telephone, no Touch-Pad)	NO	NO	CSTD 01	
DA-202 (Single-line Headset phone)	NO	NO	CSTD 01	
DA-203 (Single-line Headset phone)	NO	NO	CSTD 01	
DA-275, DAX-275 (Amplifiers)	NO	NO	CSTD 01	
DA-375 (4-wire Plug Prong amplifier)	NO	NO	CSTD 01	
DA-475 (Amplifier)	NO	NO	CSTD 01	
Data Plus			Data Plus	
ACD Console	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Datavox			Datavox	
Datavox-One	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
David Systems			David Systems	
Standard, Executive Display Sets	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Davox			Davox	
4900 (KB31-01) 5900 Station (ST100)	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
DBA Telecom			DBA Telecom	
Smartalk 2, 3, VX	A-3/4	A-3/4	CSTD 01	1
SmartCAP Console	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
DEC			DEC	
Predictive Dialer 6000 EIS	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Deka			Deka	
1100-14, 1100-26	A-8/9	A-8/9	CSHS 01	1,2
CD1600M, EL400M, EL401M	A-8/9	A-8/9	CSHS 01	1,2
HF400M, HF401M	A-8/9	A-8/9	CSHS 01	1,2
Triumph	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Delos			Delos	
2500, 2530	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Digital			Digital	
AOD Sets (ACD Appliance)	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
DND Telectronics			DND Telectronics	
3000 ACD	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Dong Jun			Dong Jun	
DJ-2905	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
DTI / Digital Technics, Inc.			DTI / Digital Technics, Inc.	
8 / 5 Agent Console	A-8/9	A-8/9	CSHS 01	2,3
Digital Turret	A-8/9	A-8/9	CSHS 01	1,2,3
1. Turret can be programmed for Electret Modular. Use one of the following: A. UI 740, setting A-3/4 B. Direct Connect, CSTD 01 2. For Direct-Connect in the handset jack order the UI 710 for handset use. 3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Dynascan			Dynascan	
Cobra 500, 514, 600, 8522, 8700	A-3/4	A-3/4	CSTD 01	1
Cobra ST401, 412, 610, 620, 710	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Entel			Entel	
UCX 3000 Console	A-8/9	A-8/9	CSHS 01	
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
eOn Communications			eOn Communications	
Millennium Digital Sets:				
6, 12, 18 Button Telephones	A-3/4	A-3/4	CSTD 01	2
30 Button Telephone	A-3/4	A-3/4	CSTD 01	1
1. Connect to dedicated modular headset jack. 2. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Ericsson Information Systems			Ericsson Information Systems	
501 / 502, 601, 631, 661, 662	A-3/4	A-3/4	CSTD 01	3
ARD - 561, 751, ASB 102	A-8/9	A-8/9	CSHS 01	1,4
DBA 180, 706, 707, MD110 Set	A-8/9	A-8/9	CSHS 01	3,4
DBC 203, 213, 531, 561, 562	A-3/4	A-3/4	CSTD 01	3
DFG 220-01, 222-01	A-3/4	A-3/4	CSTD 01	3
Dialog Analog Sets:				
3105, 3145, 3185	A-3/4	A-3/4	CSTD 01	3
Dialog Digital Sets:				
3210, 3211, 3212	A-3/4	A-3/4	CSTD 01	3
3213, 3214	A-3/4	A-3/4	CSTD 01	2
Dialog Analog Sets:				
4106	A-3/4	A-3/4	CSTD 01	3
4147, 4186	A-3/4	A-3/4	CSTD 01	2
Dialog Digital Sets:				
DBC 4220	A-3/4	A-3/4	CSTD 01	3
DBC 4222, 4223, 4224, 4334	A-3/4	A-3/4	CSTD 01	2
Dialog IP Sets:				
3413 IP, 4422 IP, 4425 IP Vision	A-3/4	A-3/4	CSTD 01	2
Dialog ISDN Set: 3310	A-3/4	A-3/4	CSTD 01	3
Ericsson "C" Maestro Radio	A-8/9	A-8/9	CSHS 01	1,4,5

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Ericsson Continued			Ericsson Continued	
MD 110 Console	A-8/9	A-8/9	CSHS 01	1,4
Prodigy Console 7700-01, 7700-05	A-8/9	A-8/9	CSHS 01	1,4
1. Needs modular to PJ 327 dual plug prong adapter SC-W478. 2. Connect to dedicated modular headset jack. 3. For Direct-Connect in the handset jack order the UI 710 for handset use. 4. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 5. Some Consoles may require a 6-wire dual plug prong amplifier. Use the SC911-15A.				
ESI / Estech Systems, Inc.			ESI / Estech Systems, Inc.	
Call Processor (Predictive Dialer)	A-3/4	A-3/4	CSTD 01	1,3
IVX C-Class, E-Class, S-Class, X-Class:	A-3/4	A-3/4	CSTD 01	3
12-Key Digital Feature Phone	A-3/4	A-3/4	CSTD 01	3
24-Key Digital Feature Phone	A-3/4	A-3/4	CSTD 01	3
48-Key Digital Feature Phone	A-3/4	A-3/4	CSTD 01	2
48-Key IP Feature Phone	A-3/4	A-3/4	CSTD 01	2
48-Key Remote IP Feature Phone	A-3/4	A-3/4	CSTD 01	2
1. Headset compatible. 2. Connect to dedicated modular headset jack. 3. For Direct-Connect in the handset jack order the UI 710 for handset use.				
e-tel Corp.			e-tel Corp.	
FreeRide VoIP Sets: FR200, FR210	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Executone Information Systems			Executone Information Systems	
Executech Digital Series Sets:				
82100, 82200, 82300, 82500	A-3/4	A-3/4	CSTD 01	1,3
82600, 82603, 83300, 83500	A-3/4	A-3/4	CSTD 01	1,3
83700, 84200, 84300, 84500	A-3/4	A-3/4	CSTD 01	1,3
84503, 84600, 84700, 84703	A-3/4	A-3/4	CSTD 01	1,3
Digital ACD Set 84100	A-3/4	A-3/4	CSTD 01	3
Élan 2882501, 2882502	A-8/9	A-8/9	CSHS 01	3,4
Encore Series Sets:				
2512505, 2512506, 2512511	A-8/9	A-8/9	CSHS 01	3,4
2512512, 2512513, 2512514	A-8/9	A-8/9	CSHS 01	3,4
2512515, 2512516, 2512517	A-8/9	A-8/9	CSHS 01	3,4
2512501, 2512502	A-8/9	A-8/9	CSHS 01	3,4
2512503, 2512504	A-8/9	A-8/9	CSHS 01	3,4
Encore CX Series Sets:				
2992501, 2992502, 2992503	A-8/9	A-8/9	CSHS 01	3,4
2992504, 2992506, 2993506	A-8/9	A-8/9	CSHS 01	3,4
Equity II Series Sets:				
2522501, 2522502, 2522504	A-8/9	A-8/9	CSHS 01	3,4
Equity III Series Sets:				
2312501, 2312502	A-8/9	A-8/9	CSHS 01	3,4
IDS Sets: Model 12, 18, 32, 64	A-3/4	A-3/4	CSTD 01	1,3
Medley 12, 18, 32, 64, 160	A-3/4	A-3/4	CSTD 01	1,3
SRX Entree, 100, 200, 400	A-8/9	A-8/9	CSHS 01	3,4
System 84: 14K / A, 17K / D	A-3/4	A-3/4	CSTD 01	1,3
System 84: 28D / D, 29K/D, A-4	A-3/4	A-3/4	CSTD 01	1,3
TAPI161	A-3/4	A-3/4	CSTD 01	1,3
Vista I, II Console	A-8/9	A-8/9	CSHS 01	2,4

Manufacturer			Manufacturer		
Appliance / Telephone / Terminal		BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Executone Continued			Executone Continued		
<ol style="list-style-type: none"> Headset compatible. Needs modular to PJ 327 dual plug prong adapter SC-W478. For Direct-Connect in the handset jack order the UI 710 for handset use. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 					
Extrom			Extrom		
612EE, 1032EE	A-3/4	A-3/4	CSTD 01		1
HMS-616, HMS-38, HMS-1032	A-8/9	A-8/9	CSHS 01		1,2
<ol style="list-style-type: none"> For Direct-Connect in the handset jack order the UI 710 for handset use. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 					
FansTel Corporation, Inc.			FansTel Corporation, Inc.		
BT-118	A-3/4	A-3/4	CSTD 01		1
BT-118B, BT-118G-TV	A-3/4	A-3/4	CSTD 01		1,2
ST118B, ST-118G, ST-218B	A-3/4	A-3/4	CSTD 01		1,3
ST-2118	A-3/4	A-3/4	CSTD 01		1,4
<ol style="list-style-type: none"> For Direct-Connect in the handset jack order the UI 710 for handset use. Has 2.5 mm headset jack. Use the CCEL 190-2 cable. Connect to dedicated modular headset jack. Connect to dedicated modular headset Jack or 2.5 mm headset jack. Use CCEL 190-2 for the 2.5 mm headset jack. 					
Fujitsu Business Systems			Fujitsu Business Systems		
9600 System Series Sets:					
DT12S, F10B, F10D,	A-3/4	A-3/4	CSTD 24		5
FT12, FT12D, FT12DS, FT24DS	A-3/4	A-3/4	CSTD 24		5
Console : 301-800-01, 02	A-8/9	A-8/9	CSHS 01		1
Digital Attendant Console	A-8/9	A-8/9	CSHS 01		1
DT100A / B, DT101B, DT200B,	A-3/4	A-3/4	CSTD 01		5
DT201B, DT10, DT12, DT24	A-3/4	A-3/4	CSTD 01		5
Focus Series Sets:					
Focus Console 960 : 301-820-02	A-8/9	A-8/9	CSHS 01		2
Focus ET 1, ET 2	A-8/9	A-8/9	CSHS 01		5,6
Focus ET10, ET11, ET15, ET20	A-3/4	A-3/4	CSTD 01		5
Focus H15H, H15D	A-8/9	A-8/9	CSHS 01		5,6
SBCS CS10, CS20, CSD	A-3/4	A-3/4	CSTD 01		5
SBCS Attendant Console	A-8/9	A-8/9	CSHS 01		3
Series III: DS20, DS20S, DS20SD	A-3/4	A-3/4	CSTD 24		5
Series III: DS32, DS32SD	A-3/4	A-3/4	CSTD 24		5
Series III HAC CT-10, 20	See Note	See Note	See Note		7
SRS ISDN Sets: 270, 1025, 1050, 2000	A-3/4	A-3/4	CSTD 01		4,5
SRS ISDN Sets: 2100, 9912, 9924	A-3/4	A-3/4	CSTD 01		4,5
SRS VoIP: SRS-i12, SRS-i24	A-3/4	A-3/4	CSTD 01		4,5
SST Set	A-8/9	A-8/9	CSHS 01		1
Starlog Console	A-8/9	A-8/9	CSHS 01		5,6
Starlog II Console	A-3/4	A-3/4	CSTD 01		5
<ol style="list-style-type: none"> Needs modular to PJ 327 dual plug prong adapter SC-W478. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. Requires Fujitsu adapter 301848-01 and transition cable 724139-02. Has both PJ 327 dual plug prong jack and modular jack. If the PJ 327 jack is used refer to note 1. Headset Compatible. 					

Manufacturer Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
---	--------------------------------	----------------------------------	---------------------------	------------------------------

Fujitsu Continued **Fujitsu Continued**

5. For Direct-Connect in the handset jack order the UI 710 for handset use.
6. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.
7. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.

GE General Electric **GE General Electric**

ProSeries Sets:				
2-9100, 2-9116, 2-9165, 2-9167	A-3/4	A-3/4	CSTD 01	5
2-9168, 2-9169, 2-9267, 2-9270	A-3/4	A-3/4	CSTD 01	5
2-9280, 2-9285, 2-9315, 2-9316	A-3/4	A-3/4	CSTD 01	5
2-9320, 2-9340, 2-9355, 2-9356	A-3/4	A-3/4	CSTD 01	5
2-9375, 2-9380, 2-9400, 2-9420	A-3/4	A-3/4	CSTD 01	5
2-9435, 2-9436, 2-9438, 2-9439	A-3/4	A-3/4	CSTD 01	5
2-9460	NO	NO	CSTD 01	4,5
2-9896, 2-9975, 2-9980	A-3/4	A-3/4	CSTD 01	5
2-9224, 2-9243, 2-9450, 2-9631	A-3/4	A-3/4	NO	1
2-9821, 2-9891, 2-9892	A-3/4	A-3/4	NO	1
2-9451	A-3/4	A-3/4	CSTD 01	2
2-9487	NO	NO	CSTD 01	4,5
Command Control Center 1401	A-8/9	A-8/9	CSHS 01	3
GE-25202RE3, GE-25403RE3	NO	NO	CCEL 190-2	4
GE-25413RE3, GE-25414GE3	A-3/4	A-3/4	NO	
GE-29385GE1, GE-29480GE1	A-3/4	A-3/4	NO	
GE-29484GE2, GE-29490GE2	A-3/4	A-3/4	NO	
GE-29897GE1, GE-29897GE2	A-3/4	A-3/4	NO	
Cordless Sets:				
GE-25802GE3, GE-25825GE3	NO	NO	CCEL 190-2	4
GE-25838GE3, GE-25859GE3	NO	NO	CCEL 190-2	4
GE-26998GE1, GE-27938GE5	NO	NO	CCEL 190-2	4

1. Requires use of the GE Adapter Cord. This cord is available from most distributors.
2. Connect to dedicated modular headset jack.
3. Needs modular to PJ 327 dual plug prong adapter SC-W478.
The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.
4. Has 2.5 mm headset jack. Use the CCEL 190-2 cable.
5. For Direct-Connect in the handset jack order the UI 710 for handset use.

GN Netcom **GN Netcom**

AT3	NO	NO	CSTD 01	
GN 4150	NO	NO	CCEL 190-2	
GN 4170 Headset Telephone	NO	NO	CCEL 190-2	
GN 7100 Headset Telephone	NO	NO	CSTD 01	
GN 7170 Cordless Headset Telephone	NO	NO	CCEL 190-2	
GN 8000, GN 8000 MPA	NO	NO	CGA 01	1
GN 8010, GN 8010 MPA	NO	NO	CGA 01	1
GN 8020, GN 8020 MPA	NO	NO	CGA 01	1
GN 8050, GN 8050 MPA	NO	NO	CGA 01	1
GN 8210	NO	NO	CGA 01	1
GN HT Two Headset Telephone	NO	NO	CSTD 01	

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
GN Netcom Continued			GN Netcom Continued	
MPA, MPA II	NO	NO	CSTD 01	1
RD3, RD3M (Rep. Not Available)	NO	NO	CSTD 01	
1. Transmit on Amplifier will need to be turned down by one or two notches.				
GST America			GST America	
HAC 2500, 2554, 4500	A-8/9	A-8/9	CSHS 01	1,2
HAC 2601, 2603	See Note	See Note		3
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 3. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.				
GTE			GTE	
SBCS CS-10, CS-20, CSD	A-3/4	A-3/4	CSTD 01	2
SBCS Attendant Console	A-8/9	A-8/9	CSHS 01	1,3
SPD701-1	See Note	See Note		4
Ultrastar Series Sets:				
2000, 2010, 2050, 2100, 2104	A-3/4	A-3/4	CSTD 01	2
2110, 2120, 2140, 2200, 2245	A-3/4	A-3/4	CSTD 01	2
2250, 2300, 2350, 2355, 2400	A-3/4	A-3/4	CSTD 01	2
7510, 7520	A-3/4	A-3/4	CSTD 01	2
1. Has both PJ 327 dual plug prong jack and modular jack. For the PJ 327 jack use the modular to PJ 327 dual plug prong adapter SC-W478. 2. For Direct-Connect in the handset jack order the UI 710 for handset use. 3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 4. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.				
Harris Digital Corp.			Harris Digital Corp.	
20/20 Console	A-8/9	A-8/9	CSHS 01	2,3
D400 / D1200 Console	A-8/9	A-8/9	CSHS 01	1
Optic Series Sets:				
780782, 780830, 780844, 780920	A-3/4	A-3/4	CSTD 01	2
780922, 780927, 780930	A-3/4	A-3/4	CSTD 01	2
Optic ACD Sets:				
780762, 780821, 780898, 780927	A-3/4	A-3/4	CSTD 01	2
ProtoCall DLS-1	A-8/9	A-8/9	CSHS 01	1
1. Needs modular to PJ 327 dual plug prong adapter SC-W478. The AIA 01 in-line amplifier with CSDT 01 cable can also be used. 2. For Direct-Connect in the handset jack order the UI 710 for handset use. 3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Hello Direct			Hello Direct	
Headset Amplifiers	See Note	See Note	See Note	1
1. Not Compatible.				
Hewlett Packard (HP)			Hewlett Packard (HP)	
HP IPAQ 2490B	See Note	See Note	See Note	1
1. Compatible CCEL 195 cable. Special order only.				

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Hitachi			Hitachi	
Attendant Console, HD100, 200	A-8/9	A-8/9	CSHS 01	1
SelecSets:				
200, 300, 400, 720, 730, 740	A-5	A-5	CHS 01	3
SelecSet 900 Series:				
SS920, SS930, SS940, SS940A	A-3/4	A-3/4	CSTD 24	2
Turret Consoles:				
HIT-E5, HIT-E6, HIT-H6	A-3/4	A-3/4	CSTD 01	3
HIT-H7, HIT-L6, HIT-L7	A-3/4	A-3/4	CSTD 01	3
1. Needs modular to PJ 327 dual plug prong adapter SC-W478. The AIA 01 in-line amplifier with CSDT 01 cable can also be used. 2. Connect to dedicated modular headset jack. 3. For Direct-Connect in the handset jack order the UI 710 for handset use.				
IBM			IBM	
412 Set	A-3/4	A-3/4	CSTD 01	2
4900 Set	NO	NO	CCEL 190-2	
IBM Attendant Console	A-8/9	A-8/9	CSHS 01	1
M-Wave, WaveRunner, WindSurfer (CTI)	NO	NO	CEDPC 1	
1. Needs modular to PJ 327 dual plug prong adapter SC-W478. The AIA 01 in-line amplifier with CSDT 01 cable can also be used. 2. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Innovative Communications			Innovative Communications	
VoicePhone 100	See Note	See Note		1
1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturer's amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.				
Intecom			Intecom	
Attendant Console-1	A-8/9	A-8/9	CSHS 01	1,4
ITE Attendant Console-2	A-8/9	A-8/9	CSHS 01	3,4
ITE Digital Telephones:				
4, 12+, 12S, 12SD, 30SD	A-3/4	A-3/4	CSTD 01	3
ITE Digital Agent	A-3/4	A-3/4	CSTD 01	2
PointSpan VoIP Sets:				
VoIP ITE-4, -12+, 12S, 12SD, -30SD	A-3/4	A-3/4	CSTD 01	3
VoIP ITE-Agent Console	A-3/4	A-3/4	CSTD 01	2
1. Needs modular to PJ 327 dual plug prong adapter SC-W478. 2. Connect to dedicated modular headset jack. 3. For Direct-Connect in the handset jack order the UI 710 for handset use. 4. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Integrated Technology			Integrated Technology	
CompuPhone 2000	A-3/4	A-3/4	CSTD 01	
Integrated Wave Technology			Integrated Wave Technology	
CTI Soundboard	NO	NO	CEDPC 1	
Interactive, Inc.			Interactive, Inc.	
Sound Xchange	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Interactive Intelligence, Inc			Interactive Intelligence, Inc.	
Customer Interaction Center (CIC)	See Note	See Note		1
Enterprise Interaction Center (EIC)	See Note	See Note		1
1. Compatibility determined by the type of single line phone used with the system.				

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Inter-Tel				Inter-Tel
Axxent Sets	A-5	A-5	CHS 01	1,3
Axxess Digital Keypad 770-4500, 770-4600	A-5	A-5	CHS 01	1,3
Axxess 4000 Series Phones:				
Axxess Basic Speaker Phone 520.4300	A-5	A-5	CHS 01	3
Axxess Standard LCD Phone 550.4000	A-5	A-5	CHS 01	1,3
Axxess Executive Phone 550.4100	A-5	A-5	CHS 01	1,3
Axxess Standard Phone 550.4300	A-5	A-5	CHS 01	1,3
Axxess Standard LCD Phone 550.4400	A-5	A-5	CHS 01	1,3
Axxess Executive Phone 550.4500	A-5	A-5	CHS 01	1,3
Axxess Digital Endpoints 8500	A-5	A-5	CHS 01	1,3
Axxess Digital Endpoints 8520, 8560	A-5	A-5	CHS 01	1,2
Axxess IP-based Endpoints 8600, 8620, 8622	A-5	A-5	CHS 01	1,3
Axxess IP-based Endpoints 8602	A-5	A-5	CHS 01	2
Axxess IP-based Endpoints 8660, 8662	A-5	A-5	CHS 01	1,3
Axxess IP-based Endpoints Multimedia 8690	A-5	A-5	CHS 01	2
Eclipse Digital Sets	A-5	A-5	CHS 01	1,3
Encore Digital Phone	A-5	A-5	CHS 01	1,3
ESP Key Sets	A-5	A-5	CHS 01	3
GLX Key Sets	A-5	A-5	CHS 01	3
GLX Plus Sets	A-5	A-5	CHS 01	1,3
GM Key Sets	A-5	A-5	CHS 01	3
GMX DVK Sets	A-5	A-5	CHS 01	1,3
GX Key Sets	A-5	A-5	CHS 01	3
HiTec 248, 412, 824, 1648	A-5	A-5	CHS 01	3
HiTec 616, 1232, 2480	A-5	A-5	CHS 01	3
IMX Sets	A-5	A-5	CHS 01	1,3
Keylux 620, 1040, 1460	A-8/9	A-8/9	CSHS 01	3,4
MPK 412T, 1032T	A-5	A-5	CHS 01	3
PC Operators Computer Console	A-5	A-5	CHS 01	1,3
Phoenix 248, 412, 824, 1648	A-5	A-5	CHS 01	3
Phoenix 616, 1232, 2480	A-5	A-5	CHS 01	3
Premier 12BTN, 18BTN	A-5	A-5	CHS 01	1,3
Premier 24BTN, 30BTN	A-5	A-5	CHS 01	1,3
SPK 1664T, 2480T	A-5	A-5	CHS 01	3
<ol style="list-style-type: none"> 1. Headset compatible. 2. Connect to dedicated modular headset jack. 3. For Direct-Connect in the handset jack order the UI 710 for handset use. 4. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 				
IPC Information Systems			IPC Information Systems	
641KS, EPC	A-8/9	A-8/9	CSHS 01	4
Centre Max 00895	A-3/4	A-3/4	CSTD 01	3
Centre Max 06088, 06089	A-8/9	A-8/9	CSHS 01	4
Centre Max 21608, 21610	A-8/9	A-8/9	CSHS 01	4
Digital Trade Net MX	A-8/9	A-8/9	CSHS 01	1,4
Exchange I, II	A-8/9	A-8/9	CSHS 01	4
Series I Turret	A-8/9	A-8/9	CSHS 01	2,4
Series II Turret	See Note	See Note		2,5
Trade Net I, II, III	A-8/9	A-8/9	CSHS 01	4

Manufacturer			Manufacturer		
Appliance / Telephone / Terminal		BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
IPC Continued				IPC Continued	
<ol style="list-style-type: none"> 1. May need modular to PJ 327 dual plug prong adapter SC-W478. 2. Needs modular to PJ 327 dual plug prong adapter SC-W478. 3. For Direct-Connect in the handset jack order the UI 710 for handset use. 4. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 5. Only compatible with another manufacturers headset amp. Check the Setup Guide for manufacturer's amplifier model in use. 					
ISDN*tek				ISDN*tek	
CTI Commuter, Commuter Plus, Enterprise		A-3/4	A-3/4	CSTD 01	1
CTI Enterprise Quad+Plus		A-3/4	A-3/4	CSTD 01	1
Cyber Space Freedom		A-3/4	A-3/4	CSTD 01	1
<ol style="list-style-type: none"> 1. For Direct-Connect in the handset jack order the UI 710 for handset use. 					
Isoetec				Isoetec	
Digital Series Sets:					
82030, 82100, 82200, 82300		A-3/4	A-3/4	CSTD 01	2
82359, 82500, 82600, 82603		A-3/4	A-3/4	CSTD 01	2
83300, 83500, 83700, 84100		A-3/4	A-3/4	CSTD 01	2
84500, 84600, 84700		A-3/4	A-3/4	CSTD 01	2
EZ-1 / Genus Series Sets:					
80100, 80300, 80304, 80500, 80700		A-3/4	A-3/4	CSTD 01	2
Operators Console : USA-001		A-3/4	A-3/4	CSTD 01	1,2
Operators Integrated CRT		A-3/4	A-3/4	CSTD 01	1,2
System 84: 14K / A, 17K / D		A-3/4	A-3/4	CSTD 01	1,2
System 84: 28D / D, 29K/D, A-4		A-3/4	A-3/4	CSTD 01	1,2
<ol style="list-style-type: none"> 1. Headset compatible. 2. For Direct-Connect in the handset jack order the UI 710 for handset use. 					
Iwatsu America				Iwatsu America	
ADIX IP Phone IX-12IPKTD		A-3/4	A-3/4	CSTD 01	2
ADIX Omega Digital Sets:					
IX-12KTD-2, IX-12KTS-2		A-3/4	A-3/4	CSTD 01	1,5
IX-12KTD-3, IX-12KTS-3		A-3/4	A-3/4	CSTD 01	2
IX-ATT Attendant Console		A-3/4	A-3/4	CSTD 01	2
IX-MKT		A-3/4	A-3/4	CSTD 01	5
BT 1530, BT 2250		A-8/9	A-8/9	CSHS 01	4,6
ET-126, ET-228		A-8/9	A-8/9	CSHS 01	5
ETD-12D / K, ETD-24D / F859		A-3/4	A-3/4	CSTD 01	3,5
ETD-6D / K, ETD-8D / K		A-3/4	A-3/4	CSTD 01	3,5
IDS Series Sets		A-3/4	A-3/4	CSTD 01	5
Omega 714 VC, 1530, 2250		A-8/9	A-8/9	CSHS 01	5,6
Omega ET 412, ET 816, ET 824		A-8/9	A-8/9	CSHS 01	5,6
Omega ET 1632, ET 2460, ET 2464		A-8/9	A-8/9	CSHS 01	5,6
Omega IV EX 616, EX 816, EX 824		A-3/4	A-3/4	CSTD 01	5
Omega IV EX 1232, EX 1648		A-3/4	A-3/4	CSTD 01	5
Omega ZT-D Sets:					
ZT-6D/6K, ZT-8D/8K		A-3/4	A-3/4	CSTD 01	5
ZT-12D/12K, ZT-12KTS		A-3/4	A-3/4	CSTD 01	3,5
ZT-12KTX, ZT-24D/24X		A-3/4	A-3/4	CSTD 01	3,5
ZT-24K, ZT-24KTS, ZT-24KTX		A-3/4	A-3/4	CSTD 01	3,5
Omega ZT-S Sets:					
ZT-6KTS, ZT-6KTD		A-3/4	A-3/4	CSTD 01	5

Manufacturer			Manufacturer		
Appliance / Telephone / Terminal		BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Iwatsu Continued			Iwatsu Continued		
<ol style="list-style-type: none"> Headset compatible. Connect to dedicated modular headset jack. If the Iwatsu SHCB-Z or SMSA-Z Headset Adapter is used, use the same selection has the handset jack. Needs modular to PJ 327 dual plug prong adapter SC-W478. For Direct-Connect in the handset jack order the UI 710 for handset use. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 					
Kanda			Kanda		
EK 616, EK 1232, EK 2064 Sets		A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.					
Key Systems U.S. / KS Telecom			Key Systems U.S. / KS Telecom		
Atlas ET 16, ET 36		A-3/4	A-3/4	CSTD 01	1
Atlas ET 4, ET 15		A-3/4	A-3/4	CSTD 01	1
Atlas Digital Sets		A-3/4	A-3/4	CSTD 01	1
Atlas Universal		A-3/4	A-3/4	CSTD 01	1
KSX 32 / 128 Console		A-3/4	A-3/4	CSTD 01	1
Salta Set		A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.					
Lennox Electronics Corp.			Lennox Electronics Corp.		
PH 319, PH 321, PH 322		A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.					
Lexar			Lexar		
LX-2, LX-5, LX-15, LX-20		See Note	See Note		3
LX-2010, LX-2011, LX-2020		A-8/9	A-8/9	CSHS 01	1,2
LX-2021, LX-2031, LX-3014		A-8/9	A-8/9	CSHS 01	1,2
LX-3021, LX-3037		A-8/9	A-8/9	CSHS 01	1,2
LX-AC-ATT 2000 Console		A-8/9	A-8/9	CSHS 01	1,2
LX-Attendant Console		A-3/4	A-3/4	CSTD 01	1
TLX-2, TLX-5, TLX-15		See Note	See Note		3
TLX-15HLS, TLX-15ZS		See Note	See Note		3
TLX-AA, TLX-AC Attendant Console		See Note	See Note		3
<ol style="list-style-type: none"> For Direct-Connect in the handset jack order the UI 710 for handset use. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 					
Linksys			Linksys		
Linksys PHM 1100, PHM 1200		A-3/4	A-3/4	CSTD 01	2
Linksys -Cisco SPA-941		See Note	See Note	See Note	1
Linksys Sipura SPA-841		See Note	See Note	See Note	1
Linksys SPA 921, SPA 922		See Note	See Note	See Note	1
Linksys SPA 941, SPA 942, SPA 962		See Note	See Note	See Note	1
<ol style="list-style-type: none"> Has 4-Pole, 2.5 mm headset jack. Use Sennheiser standard MM Series Headsets. Connect to dedicated modular headset jack. 					
Lucent Technologies			Lucent Technologies		
Next Generation iPhones:					
a2011, a2011-2, i2021, i2022		A-3/4	A-3/4	CSTD 01	1,2

Manufacturer			Manufacturer		
Appliance / Telephone / Terminal		BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Lucent Continued			Lucent Continued		
<p>1. Has 3.5 mm (3/8") headset jack. Lucent recommends the Tele-Infonet headset adapter cord # CC 300316668 for Universal Amplifiers. Radio Shack also has a adapter P/N 274-397 that the CCEL 190-2 cable can plug into.</p> <p>2. For Direct-Connect in the handset jack order the UI 710 for handset use.</p>					
Macrotel			Macrotel		
Excel 308E, 816E	See Note	See Note	See Note		1
MT-3T, MT-3TX, MT- 5T, MT-5TX	See Note	See Note	See Note		1
MT-8T, MT-8TX, MT-12T, MT-12TX	See Note	See Note	See Note		1
MT-12H, MT-14H, MT-16H, MT-20D	See Note	See Note	See Note		1
MT-24T, MT-24TX, MT-30X	See Note	See Note	See Note		1
MTH Sets	See Note	See Note	See Note		1
MTX Sets	See Note	See Note	See Note		1
<p>1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.</p>					
Mitel Networks			Mitel Networks		
5001 IP, 5005 IP Phone	A-3/4	A-3/4	CSTD 01		1
5010 IP, 5020 IP, 5021 IP Phone	A-3/4	A-3/4	CSTD 01		1
5140 IP, 5212 IP, 5215 IP	A-3/4	A-3/4	CSTD 01		1
5220 IP, 5224 IP, 5230 IP	A-3/4	A-3/4	CSTD 01		1
5550 IP Console	A-3/4	A-3/4	CSTD 01		2
Consoles: 1000, 1001, 1003	A-3/4	A-3/4	CSTD 01		2
SuperConsole 1000, 2000	A-3/4	A-3/4	CSTD 01		2
SuperSet 1, 2, 3, 4, 7	A-3/4	A-3/4	CSTD 01		2
SuperSet 401, 410, 420, 430	A-3/4	A-3/4	CSTD 01		2
SuperSet 4001	A-3/4	A-3/4	CSTD 01		2
SuperSet 4015, 4025, 4125, 4150	A-3/4	A-3/4	CSTD 01		1,3
SuperSet 700 / PC Phone	A-3/4	A-3/4	CSTD 01		1
SuperSet 7000 / PC-Attendant	A-3/4	A-3/4	CSTD 01		1
SX200 Digital Super Console	A-3/4	A-3/4	CSTD 01		2
<p>1. Connect to dedicated modular headset jack. The "AMS 01" is not recommended as it may disconnect the call when activated.</p> <p>2. For Direct-Connect in the handset jack order the UI 710 for handset use.</p> <p>3. Handset microphone is disabled with headset plugged in. To use the handset Easy Disconnect the headset top from the connecting cable.</p>					
Modular Communication Systems			Modular Communication Systems		
Mod-U-Com Console	A-8/9	A-8/9	CSHS 01		1,2,3
<p>1. Needs modular to PJ 327 dual plug prong adapter SC-W478.</p> <p>2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.</p> <p>3. Some Consoles may require a 6-wire dual plug prong amplifier. Use the SC911-15A.</p>					
Motorola			Motorola		
911 SRX Set	A-8/9	A-8/9	CSHS 01		5
B1630 Console	A-8/9	A-8/9	CSHS 01		1,5,6
C100 Controller	A-3/4	A-3/4	CSTD 01		
Centracom I, II & III	A-8/9	A-8/9	CSHS 01		1,5,6
CentraLink 911	A-8/9	A-8/9	CSHS 01		1,5,6
DGT9000 Desktop Controller	A-3/4	A-3/4	CSTD 01		
Elite Golden Centracom	A-8/9	A-8/9	CSHS 01		1,5,6

Manufacturer Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
Motorola Continued				Motorola Continued
Flexar Base Station	A-8/9	A-8/9	CSHS 01	1,5,6
Golden Centracom II	A-8/9	A-8/9	CSHS 01	1,5,6
53677 Cordless Phone	NO	NO	CCEL 190-2	
MA362 Cordless Phone	NO	NO	CCEL 190-2	
MAXAR 80	A-8/9	A-8/9	CSHS 01	5
Mitrex Super Console	A-8/9	A-8/9	CSHS 01	1,5,6
MSD 5000 Console	A-8/9	A-8/9	CSHS 01	1,2,5,6
STU III (1000 Voice Data Terminal)	A-3/4	A-3/4	CSTD 01	
T-Series Consoles:				
T1600, T1602, T1603, T1604	A-8/9	A-8/9	CSHS 01	1,2,5,6
T1605, T1606, T1609, T1617	A-8/9	A-8/9	CSHS 01	1,2,5,6
T5600 Console	A-8/9	A-8/9	CSHS 01	3,5
Talkabout 270, 280	NO	NO	CCEL 190-2	4
Talkabout T289, T300P, T5100, T5200	NO	NO	CCEL 190-2	4
Talkabout T5300, T5320, T5400, T5420	NO	NO	CCEL 190-2	4
Talkabout T5600, T5620, T5700, T5710	NO	NO	CCEL 190-2	4
Talkabout T5720, T6200, T6220, T6300	NO	NO	CCEL 190-2	4
Talkabout T6320, T6400, T7200	NO	NO	CCEL 190-2	4
Vesta Pallas E9-1-1 with:				
Vesta / CENTRACOM Elite Console	A-8/9	A-8/9	CSHS 01	1,5,6
Vesta / MCC 5500 Console	A-8/9	A-8/9	CSHS 01	1,5,6
XTS 3000	NO	NO	NO	7
<ol style="list-style-type: none"> Needs modular to PJ 327 dual plug prong adapter SC-W478. Requires use of Motorola # BLNT6223A-CS-5 headset interface box. May need modular to PJ 327 dual plug prong adapter SC-W478. Has 3.5 mm (3/8") headset jack. Radio Shack has a 2.5 mm to 3.5 mm adapter P/N 274-397 that the CCEL 190-2 cable can plug into. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. Some Consoles may require a 6-wire dual plug prong amplifier. Use the SC911-15A. Not compatible. 				
Multilink, Inc.				Multilink, Inc.
Conference Bridge	A-8/9	A-8/9	CSHS 01	1
1. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Murata				Murata
FAX Phone 625M, 655M, 750M	A-3/4	A-3/4	CSTD 01	1
FAX Phone F-76, F-86	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
National Telecom / Solid State Systems			National Telecom / Solid State Systems	
ACD IV : 113-6064	A-3/4	A-3/4	CSTD 01	2
ACDII Agent Set	A-8/9	A-8/9	CSHS 01	1,3
ECD 2B/2C Consoles	A-8/9	A-8/9	CSHS 01	1,3
JR Executive 116-6502, 117-6526	A-3/4	A-3/4	CSTD 01	2
<ol style="list-style-type: none"> Needs modular to PJ 327 dual plug prong adapter SC-W478. For Direct-Connect in the handset jack order the UI 710 for handset use. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 				
Natural Microsystems				Natural Microsystems
QX2000 / Unity I Board (sound board)	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				

Manufacturer Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
NEC America				NEC America
DSX Aspire Series Phones:				
2 Button, 22 Button, 34 Button, 34 Button IP	A-3/4	A-3/4	CSTD 01	2
DSX 300	A-3/4	A-3/4	CSTD 01	2
DS 1000, DS 2000 Sets	A-3/4	A-3/4	CSTD 01	1,9
DTerm 3000	A-3/4	A-3/4	CSTD 01	9
DTerm Series II Sets: ETE-1HM-2, ETE-1-2, ETE-6-2, ETE-6D-2, ETE-16-2, ETE-16D-2	A-3/4	A-3/4	CSTD 01	9
DTerm Series III:				
ETJ-1-1	A-3/4	A-3/4	CSTD 01	9
ETJ-8-1, ETJ-16-D-2, ETJ-16-DC-1	A-3/4	A-3/4	CSTD 01	5,9
ETJ-16-DD-1, ETJ-16-DD-2, ETJ-24-DS-1	A-3/4	A-3/4	CSTD 01	5,9
Electra Series Sets:				
ET-4R-2P, ET-4T-2P, ET-4R-3P	A-8/9	A-8/9	CSHS 01	8,9
ET-4T-3P, ET-8-1, ET-8-2	A-8/9	A-8/9	CSHS 01	8,9
ET-14-2, ET-14-3, ET-14-4, ET-14-5	A-8/9	A-8/9	CSHS 01	8,9
ET-16-1, ET-16-2, ET-16H-1, ET20-1	A-8/9	A-8/9	CSHS 01	8,9
ET-6-1, ET-6-2, ET-6-3, ET-6-1P	A-3/4	A-3/4	CSTD 01	9
ET-6-3P, ET-6H-1, ET-6H-3, ET-6H-1P	A-3/4	A-3/4	CSTD 01	2
ET-6H-3P, ET-8-3, ET-8-4, ET-8-3P	A-3/4	A-3/4	CSTD 01	2
ET-8-4P, ET-16-3, ET-16-4, ET-16-3P	A-3/4	A-3/4	CSTD 01	2
ET-16-4P, ET-16D-3, ET-16D-4, ET-16H-3	A-3/4	A-3/4	CSTD 01	2
ET-16H-4, ET-16H-3P, ET-16H-4P	A-3/4	A-3/4	CSTD 01	2
ET-16H-4, ET-16H-3P, ET-16H-4P	A-3/4	A-3/4	CSTD 01	2
Electra 824: ETZ-16-1, ETZ-16D-1	A-3/4	A-3/4	CSTD 01	2
Electra Elite IPK Series Sets:				
DTH-8-1, DTH-8D-2, DTH-16D-1, DTH-16LD-1,	A-3/4	A-3/4	CSTD 01	2
DTH-16LCD, DTH-32D-1	A-3/4	A-3/4	CSTD 01	2
Electra Elite Series Sets:				
DTU-8-1, DTU-16-1, DTU-16D-1,	A-3/4	A-3/4	CSTD 01	2
DTU-16D-2, DTU-32-1, DTU-32D-1	A-3/4	A-3/4	CSTD 01	2
HA 610Z, HA 710Z ATTCOM	A-8/9	A-8/9	CSHS 01	7,8
HA 750Z HDAC, HA 751Z HDAC	A-8/9	A-8/9	CSHS 01	7,8
HA 752Z HDAC	A-8/9	A-8/9	CSHS 01	7,8
Impulse Series Sets:				
ACD Terminal: ETT-16S-1	A-3/4	A-3/4	CSTD 01	9
DTerm 10: ETT-X-1 Executive	A-3/4	A-3/4	CSTD 01	9
DTerm 2: ETT-1-1, ETT-1-2	A-3/4	A-3/4	CSTD 01	9
DTerm 4: ETT-4-1	A-3/4	A-3/4	CSTD 01	9
DTerm 4B: ETT-8-1	A-3/4	A-3/4	CSTD 01	9
DTerm 5: ETT-16-1	A-3/4	A-3/4	CSTD 01	9
DTerm 500: ETT-D-1	A-8/9	A-8/9	CSHS 01	7,8
Mark II Series Sets:				
ETE-6-1, ETE-6D-1, ETE-16D-1	A-3/4	A-3/4	CSTD 01	3
ETE-16D-2, ETE-16K-1	A-3/4	A-3/4	CSTD 01	3
Neax 1200 Console	A-3/4	A-3/4	CSTD 01	9
Neax HDAC-A Series I & II Consoles	A-8/9	A-8/9	CSHS 01	7,8
Neax SN619, SN716, 2400 Consoles	A-8/9	A-8/9	CSHS 24	8,9
2100i	A-3/4	A-3/4	CSTD 01	9
HA 752Z HDAC	A-8/9	A-8/9	CSHS 01	7,8

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
NEC Continued			NEC Continued	
Dterm Series E Sets:				
DTP-2D-1	A-3/4	A-3/4	CSTD 01	9
DTP-8-1, DTP-8D-1, DTP-16D-1, DTP-32D-1	A-3/4	A-3/4	CSTD 01	2
Dterm Series i Sets:				
DTR-2D-1, DTR8-1, DTR-8D-1	A-3/4	A-3/4	CSTD 01	2
DTR-16D-1, DTR-32D-1	A-3/4	A-3/4	CSTD 01	2
Dterm IP ITR-8D, ITR-16D-2, ITR-32D-3	A-3/4	A-3/4	CSTD 01	2
Professional Series Sets:				
ETW-8-1, ETW-8-2, ETW-16-1	A-3/4	A-3/4	CSTD 01	3,4,9
ETW-16-2, ETW-24-1	A-3/4	A-3/4	CSTD 01	4,9
<ol style="list-style-type: none"> Headset compatible. Connect to dedicated modular headset jack. If NEC Headset Adapter ADA or ADA-1 is used, use the same selection has the handset jack. There is an inconsistency in some of the NEC sets. If there is receive and no transmit, select one of the following: <ul style="list-style-type: none"> A. Active UI setting, A-3/4. B. Direct Connect, CSTD 24 If NEC Headset Adapter ADA-J used select one of the following: <ul style="list-style-type: none"> A. Active UI setting, A-3/4. B. Direct Connect, CSTD 24 Needs modular to PJ 327 dual plug prong adapter SC-W478. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. For Direct-Connect in the handset jack order the UI 710 for handset use. 				
Newtronix Communications			Newtronix Communications	
Success Set CU 4004, CU4005, CU4006	A-3/4	A-3/4	CSTD 01	1
<ol style="list-style-type: none"> For Direct-Connect in the handset jack order the UI 710 for handset use. 				
Nitsuko America Corp.			Nitsuko America Corp.	
124i / 384i Digital Sets	See Note	See Note		3
DS01 Series Sets:				
88661, 88662, 88663, 88670, 88673	A-3/4	A-3/4	CSTD 01	2
Onyx Series Sets:				
88154, 88155, 88160	A-3/4	A-3/4	CSTD 01	2
88163, 88250, 88260	A-3/4	A-3/4	CSTD 01	2
88261, 88263, 88350	A-3/4	A-3/4	CSTD 01	2
88360, 88361, 88363	A-3/4	A-3/4	CSTD 01	2
Optima Series Sets	A-3/4	A-3/4	CSTD 01	2
Portrait Sets	See Note	See Note		3
<ol style="list-style-type: none"> Headset compatible. For Direct-Connect in the handset jack order the UI 710 for handset use. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 				
Norstan			Norstan	
Advantage I Sets	A-3/4	A-3/4	CSTD 01	1,3
Advantage II Sets	A-3/4	A-3/4	CSTD 01	2,3
<ol style="list-style-type: none"> Headset compatible. If the Norstan SHCB-Z or SMSA-Z Headset Adapter is used, use the same selection as the handset jack. For Direct-Connect in the handset jack order the UI 710 for handset use. 				

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Nortel Networks			Nortel Networks	
Agent Console NT4X09AG, NT4X09BB	A-8/9	A-8/9	CSHS 01	6,10
Attendant Console M1109 QSU71	A-3/4	A-3/4	CSTD 01	11
Attendant Console M1250 NT2G00A-35	A-8/9	A-8/9	CSHS 01	6,10
Attendant Console M1309 QSU73	A-3/4	A-3/4	CSTD 01	11
Attendant Console M2250 NT6G00AA-35	A-3/4	A-3/4	CSTD 01	6,7
Attendant Console QCW2, QCW3	A-8/9	A-8/9	CSHS 01	6,10
Attendant Console QCW4, QCW5	A-8/9	A-8/9	CSHS 01	6,10
IP1110	A-3/4	A-3/4	CSTD 01	11
IP1120E	A-3/4	A-3/4	CSTD 01	1
IP1140E, IP1150E	A-3/4	A-3/4	CSTD 01	1,12
IP 1210	A-3/4	A-3/4	CSTD 01	11
IP 1220, IP 1230	A-3/4	A-3/4	CSTD 01	1
IP 1535	A-3/4	A-3/4	CSTD 01	11
IP Phone 2001 (i2001), IP Phone 2002 (i2002)	A-3/4	A-3/4	CSTD 01	11
IP Phone 2004 (i2004), IP Phone 2007 (i2207)	A-3/4	A-3/4	CSTD 01	1
IP Phone 2033 (i2033)	A-3/4	A-3/4	CSTD 01	1
IP Softphone 2050 (i2050)	A-3/4	A-3/4	UUSB 2	2
LG-Nortel IP 6804	A-3/4	A-3/4	CSTD 01	11
LG-Nortel IP 6812, IP 6830	A-3/4	A-3/4	CSTD 01	11,13
LG-Nortel IP 8501, IP 8540	A-3/4	A-3/4	CSTD 01	1
Mobile USB Headset Adapter for IP Softphones	See Note	See Note	See Note	13
WLAN Handset 2210, 2211, 2212	See Note	See Note	See Note	13
WLAN Handset 6120, 6140	See Note	See Note	See Note	13
Jazz 1400, 1420, 1440, 1460	A-3/4	A-3/4	CSTD 01	11
Jazz 1600, 1650, 4000	A-3/4	A-3/4	CSTD 01	11
Maestro 1500, 1500 EV, 1500CW	A-3/4	A-3/4	CSTD 01	11
Maestro 2500, 3500, 3500 CW	A-3/4	A-3/4	CSTD 01	11
Meridian Consoles:				
QSU 1, QSU 3, QSU 6, QSU 7	A-8/9	A-8/9	CSHS 01	10,11
QSU 60, QSU 61	A-8/9	A-8/9	CSHS 01	6,10
QSU 63, QSU 67	A-8/9	A-8/9	CSHS 01	10,11
Meridian Sets:				
M2006 (NTZK06, NT2K06) (NT9K05)	A-5	A-5	CHS 01	11
M2008 (NTZK08, NT2K08) (NT9K08)	A-5	A-5	CHS 01	11
M2009 (NT1F05)	A-5	A-5	CHS 01	11
M2016 (NTZK20, NT2K20)	A-5	A-5	CHS 01	11
M2018 (NT1F07)	A-5	A-5	CHS 01	11
M2112 (NT1F06)	A-5	A-5	CHS 01	11
M2216 ACD I (NTZK18, NT2K18) (NT9K18)	A-5	A-5	CHS 01	3
M2216 ACD I (NTZK22, NT2K22)	A-5	A-5	CHS 01	3
M2216 ACD II (NTZK23, NT2K23)	A-5	A-5	CHS 01	4
Meridian M2317 NT1F21	A-5	A-5	CHS 01	1,11
M2616 (NTZK16, NT2K16, NT9K16)	A-5	A-5	CHS 01	11
Meridian M3000 (NT1F11), M4000	A-5	A-5	CHS 01	11
Meridian Digital Sets:				
M3901, M3902	A-3/4	A-3/4	CSTD 01	11
M3903, M3904, M3905	A-3/4	A-3/4	CSTD 01	1

Manufacturer	Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer	Notes
Nortel Continued		Nortel Continued				
Meridian II Sets:						
M5008 (NT4X40), M5208 (NT4X41)		A-3/4	A-3/4	CSTD 01		11
M5216 (NT4X44)		A-3/4	A-3/4	CSTD 01		1
M5316 (NT4X42)		A-3/4	A-3/4	CSTD 01		11
Meridian P-Phones:						
M5006 (NT4X21), M5009 (NT4X35)		A-3/4	A-3/4	CSTD 01		11
M5112 (NT4X31), M5209 (NT4X36, NT4X38)		A-3/4	A-3/4	CSTD 01		11
M5212 (NT4X39)		A-3/4	A-3/4	CSTD 01		5
M5312, M5317 (NT4X37)		A-3/4	A-3/4	CSTD 01		11
Meridian Unity Series Sets:						
M8003 NT2N57, M8009 NT2N24		A-3/4	A-3/4	CSTD 01		11
M8314 NT2N30, M8417 NT2N32		A-3/4	A-3/4	CSTD 01		11
M9009 NT2N74, M9216 NT2N33		A-3/4	A-3/4	CSTD 01		11
M9316 NT2N31		A-3/4	A-3/4	CSTD 01		11
M9417 NT2N36, M9516 NT2N42		A-3/4	A-3/4	CSTD 01		8,11
Norstar Sets:						
M7100 (NT8B14)		A-3/4	A-3/4	CSTD 01		11
M7208 (NT8B20), M7310 (NT8B30)		A-3/4	A-3/4	CSTD 01		1
M7324 (NT8B40), M7900 (NT8B50)		A-3/4	A-3/4	CSTD 01		1
Quick Touch 100, 200		A-3/4	A-3/4	CSTD 01		11
Rappert, Rappert Plus		A-3/4	A-3/4	CSTD 01		11
Norstar Business Terminals:						
T7100		A-3/4	A-3/4	CSTD 01		11
T7208, T7316		A-3/4	A-3/4	CSTD 01		1
T7324		A-3/4	A-3/4	CSTD 01		11
T7406 Wireless Phone		NO	NO	CCEL 190-2		
Nortel Multimedia Conferencing		A-3/4	A-3/4	CSTD 01		11
Power Touch 225, 250, 350, 452		A-3/4	A-3/4	CSTD 01		11
Unity Series Sets:						
NT1K00, NT1K02, NT4L15, NT4L17		A-3/4	A-3/4	CSTD 01		11
NT4L20, NT4L21, NT6K00, NT6K7		A-3/4	A-3/4	CSTD 01		11
NT6K10, NT6K90		A-3/4	A-3/4	CSTD 01		11
Unity I 8100 NT4L11		A-3/4	A-3/4	CSTD 01		11
Unity II 8200 NT4L12		A-3/4	A-3/4	CSTD 01		11
Unity III 8300 NT4L01		A-3/4	A-3/4	CSTD 01		9,11
Unity VII 8400 NT4L10		A-3/4	A-3/4	CSTD 01		11
Unity XX 8600 NT4L04		A-3/4	A-3/4	CSTD 01		11
Unity XX 8600 NT4L14		A-3/4	A-3/4	CSTD 01		11
Vantage		A-3/4	A-3/4	CSTD 01		11
Vantage Esprit / Esprit Plus		A-3/4	A-3/4	CSTD 01		11
Venture NT2N81		A-3/4	A-3/4	CSTD 01		11
Vista 350 NT2N52		A-3/4	A-3/4	CSTD 01		11
<ol style="list-style-type: none"> 1. Connect to dedicated modular headset Jack. 2. May need the Nortel Networks "BCM USB" or the Mobile BCM USB Audio Kit for headset use. 3. Phone should be programmed to headset "Option 2". 4. Use the modular Jack for the headset not the PJ 327 dual plug prong Jack. 5. Phone has two headset Jacks on the back. Plug the headset into the Jack with the icon of a headset only. Not the Jack that has an icon of a headset with dual plug prongs. 						

Manufacturer	Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
--------------	----------------------------------	--------------------------------	----------------------------------	---------------------------	-----------------------

Nortel Continued					Nortel Continued
<p>6. Needs modular to PJ 327 dual plug prong adapter SC-W478.</p> <p>7. The Handset of the M2250 console can not be plugged into the console at the same time the headset is plugged in.</p> <p>8. Headset compatible.</p> <p>9. The switch on the bottom of the phone needs to be placed in position "C".</p> <p>10. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.</p> <p>11. For Direct-Connect in the handset jack order the UI 710 for handset use.</p> <p>12. Bluetooth enabled for use with wireless Bluetooth headset.</p> <p>13. Has 2.5 mm headset jack. Use the CCEL 190-2 cable.</p>					

Northcom				Northcom
ESP Series Sets:				
612, 1224, 2460	See Note	See Note	See Note	3
Premier 1A3 Set	A-3/4	A-3/4	CSTD 01	2
Premier Series Sets:				
2500, DHK	A-8/9	A-8/9	CSHS 01	1,2
308, 616, 1648	A-8/9	A-8/9	CSHS 01	1,2
<p>1. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.</p> <p>2. For Direct-Connect in the handset jack order the UI 710 for handset use.</p> <p>3. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.</p>				

Northwestern Bell				Northwestern Bell
Answermate Series Sets:				
1500, 1600, 61160, 61170	A-3/4	A-3/4	CSTD 01	1
Basic Series Sets:				
51290, 51450, 51460, 51530, 51570	A-3/4	A-3/4	CSTD 01	1
Competitor Series Sets:				
21410, 21420, 21430	A-3/4	A-3/4	CSTD 01	1
Easy Reach Series Sets:				
81100, 81200, 81100, 81200	A-3/4	A-3/4	CSTD 01	1
Easy Touch Series Sets:				
22411, 22455, 26001, 26002, 43600	A-3/4	A-3/4	CSTD 01	1
Integra Series Sets:				
75000, 75005, 78002, 78003	A-3/4	A-3/4	CSTD 01	1
Techline Series Sets:				
220 (77002), 420 (77004)	A-3/4	A-3/4	CSTD 01	1
2000 (24900), 2700 (24910)	A-3/4	A-3/4	CSTD 01	1
2700S (24920), 2702S (24930)	A-3/4	A-3/4	CSTD 01	1
Traditional Series Sets:				
51280, 51550	A-3/4	A-3/4	CSTD 01	1
<p>1. For Direct-Connect in the handset jack order the UI 710 for handset use.</p>				

OKI				OKI
Discovery 3	A-8/9	A-8/9	CSHS 01	1,2
OKI-3532	A-3/4	A-3/4	CSTD 01	3
Spectrum 100	A-8/9	A-8/9	CSHS 01	2,3
Spectrum 400, 700	A-8/9	A-8/9	CSHS 01	1,2
<p>1. Needs modular to PJ 327 dual plug prong adapter SC-W478.</p> <p>2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.</p> <p>3. For Direct-Connect in the handset jack order the UI 710 for handset use.</p>				

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Ontario Systems			Ontario Systems	
Predictive Dialer Guaranteed Contact	A-8/9	A-8/9	CSHS 01	1,2
1. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
2. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Orbacom Systems			Orbacom Systems	
Calida Console, Calida Plus Console	A-8/9	A-8/9	CSHS 01	1,2,3
CRT-TDM-150 Console	A-8/9	A-8/9	CSHS 01	1,2,3
TRM-150 Console	A-8/9	A-8/9	CSHS 01	1,2,3
1. Needs modular to PJ 327 dual plug prong adapter SC-W478.				
2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
3. Some Consoles may require a 6-wire dual plug prong amplifier. Use the SC911-15A.				
Page Industries			Page Industries	
Headset Amplifier: PI-AMP	NO	NO	CSTD 01	1
1. Has 2.5 mm headset jack. Use the CCEL 190-2 cable.				
palmOne			palmOne	
Treo 600, Treo 650	NO	NO	CCEL 190-2	
Panasonic			Panasonic	
DBS Series Sets:				
VB 43210, VB 43220, VB 43221, VB 43223	A-8/9	A-8/9	CSHS 24	1,4,5
VB 43225, VB 43230, VB 43231, VB 43233	A-8/9	A-8/9	CSHS 24	1,4,5
VB 43310, VB 43320, VB 44210, VB 44223	A-8/9	A-8/9	CSHS 24	1,4,5
VB 44225, VB44230	A-8/9	A-8/9	CSHS 24	1,4,5
Digital Series Sets:				
KX-T 7130, KX-T 7220, KX-T 7230	A-3/4	A-3/4	CSTD 24	1,5
KX-T 7235, KX-T 7250	A-3/4	A-3/4	CSTD 24	1,5
Digital Super Hybrid Series Sets (XDP):				
KX-T 7420, KX-T 7425, KX-T 7431	A-3/4	A-3/4	CSTD 24	3,5
KX-T 7433, KX-T 7436, KX-T 7453	A-3/4	A-3/4	CSTD 24	3,5
KX-T 7456	A-3/4	A-3/4	CSTD 24	3,5
KX-T 7720, KX-T 7730, KX-T 7735	A-3/4	A-3/4	CSTD 24	3,5
KX-T 7740, KX-T 7750	A-3/4	A-3/4	CSTD 24	3,5
Digital Hybrid IP-PBX Series Sets:				
KX-T 7625, KS-T 7630	A-3/4	A-3/4	CSTD 24	3,5
KX-T 7633, KX-T 7636	A-3/4	A-3/4	CSTD 24	3,5
KX-TA 308 Advanced Hybrid Series Sets:				
KX-TA 30820, KX-TA 30830, KX-TA 30850	A-3/4	A-3/4	CSTD 24	3,5
Ease-A-Phone Series Sets:				
KX-D 4130, KX-D 4985	A-3/4	A-3/4	CSTD 24	5
KX-T 2010, KX-T 2120, KX-T 2130	A-3/4	A-3/4	CSTD 24	5
KX-T 2131, KX-T 2135, KX-T 2140	A-3/4	A-3/4	CSTD 24	5
KX-T 2150, KX-T 2155, KX-T 2165	A-3/4	A-3/4	CSTD 24	5
KX-T 2180, KX-T 2220, KX-T 2221	A-3/4	A-3/4	CSTD 24	5
KX-T 2250, KX-T 2260, KX-T 2310	A-3/4	A-3/4	CSTD 24	5
KX-T 2315, KX-T 2320, KX-T 2322	A-3/4	A-3/4	CSTD 24	5
KX-T 2325, KX-T 2330, KX-T 2335	A-3/4	A-3/4	CSTD 24	5
KX-T 2340, KX-T 2341, KX-T 2342	A-3/4	A-3/4	CSTD 24	5
KX-T 2345, KX-T 2346, KX-T 2355	A-3/4	A-3/4	CSTD 24	5
KX-T 2356, KX-T 2360, KX-T 2365	A-3/4	A-3/4	CSTD 24	5
KX-T 2380, KX-T 2390, KX-T 2395	A-3/4	A-3/4	CSTD 24	5
KX-T 2410, KX-T 2415, KX-T 2420	A-3/4	A-3/4	CSTD 24	5
KX-T 2421, KX-T 2422, KX-T 2425	A-3/4	A-3/4	CSTD 24	5

Manufacturer	Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer	Notes
Panasonic Continued		Panasonic Continued				
KX-T 2427, KX-T 2429, KX-T 2432		A-3/4	A-3/4	CSTD 24		5
KX-T 2460, KX-T 2465, KX-T 2620		A-3/4	A-3/4	CSTD 24		5
KX-T 2622, KX-T 2630, KX-T 2632		A-3/4	A-3/4	CSTD 24		5
KX-T 2634, KX-T 2640, KX-T 2710		A-3/4	A-3/4	CSTD 24		5
KX-T 2720, KX-T 2740, KX-T 2840		A-3/4	A-3/4	CSTD 24		5
KX-T 2850, KX-T 2880, KX-T 3110		A-3/4	A-3/4	CSTD 24		5
KX-T 3120, KX-T 3122, KX-T 3130		A-3/4	A-3/4	CSTD 24		5
KX-T 3135, KX-T 3142, KX-T 3145		A-3/4	A-3/4	CSTD 24		5
KX-T 3150, KX-T 3155, KX-T 3160		A-3/4	A-3/4	CSTD 24		5
KX-T 3165, KX-T 3170, KX-T 3175		A-3/4	A-3/4	CSTD 24		5
KX-T 3185, KX-T 3220, KX-T 3250		A-3/4	A-3/4	CSTD 24		5
KX-T 3280		A-3/4	A-3/4	CSTD 24		5
KX-T 7020, KX-T 7030, KX-T 7050		A-3/4	A-3/4	CSTD 24		2,5
KX-T 7055		A-3/4	A-3/4	CSTD 24		2,5
KX-T7731, KX-T7736		A-3/4	A-3/4	CSTD 24		3,5
KX-T 616 Series Sets:						
KX-T 61620, KX-T 61630, KX-T 61631		A-3/4	A-3/4	CSTD 24		5
KX-T 61650		A-3/4	A-3/4	CSTD 24		1,5
KX-T 1232 Series Sets:						
KX-T 123220, KX-T 123221, KX-T 123230		A-3/4	A-3/4	CSTD 24		5
KX-T 123235, KX-T 123250		A-3/4	A-3/4	CSTD 24		5
Telephones including Cordless Handset:						
KX-TG 2000, KX-TG 2584, KX-TG 2750		A-3/4	A-3/4	CSTD 24		3,5
KX-TG 2770, KX-TG 4000, KX-TG-5100		A-3/4	A-3/4	CSTD 24		3,5
KX-TG 5110, KX-TG 5240, KX-TGA 420B		A-3/4	A-3/4	CSTD 24		3,5
Cordless Telephones:						
KX-TC 1484		NO	NO	CCEL 190-2		3
KX-TG 273, KX-TG 2208, KX-TG 2214		NO	NO	CCEL 190-2		3
KX-TG 2216, KX-TG 2224, KX-TG 2226		NO	NO	CCEL 190-2		3
KX-TG 2227, KX-TG 2235, KX-TG 2237		NO	NO	CCEL 190-2		3
KX-TG 2239, KX-TG 2247, KX-TG 2248		NO	NO	CCEL 190-2		3
KX-TG 2239, KX-TG 2247, KX-TG 2248		NO	NO	CCEL 190-2		3
KX-TG 2257, KX-TG 2258,		NO	NO	CCEL 190-2		3
KX-TG 2267, KX-TG 2352, KX-TG 2382		NO	NO	CCEL 190-2		3
KX-TG 2481, KX-TG 2553,		NO	NO	CCEL 190-2		3
KX-TG 2563, KX-TG 2583, KX-TG 2593		NO	NO	CCEL 190-2		3
KX-TG 2700, KX-TG 2720, KX-TG 2730		NO	NO	CCEL 190-2		3
KX-TG 2740, KX-TG 5055, KX-TG 5100		NO	NO	CCEL 190-2		3
KX-TG 5110, KX-TG 5202, KX-TG 5210		NO	NO	CCEL 190-2		3
KX-TG 5212, KX-TG 5230, KX-TG 5480		NO	NO	CCEL 190-2		3
KX-TG 6500, KX-TG 6502		NO	NO	CCEL 190-2		3
KX-TG 6700, KXTG 6702		NO	NO	CCEL 190-2		3
KX-TGA 230, KX-TGA 510		NO	NO	CCEL 190-2		3
KX-TGA 520, KX-TGA 560		NO	NO	CCEL 190-2		3
KX-TGA 650, KX-TGA 670		NO	NO	CCEL 190-2		3
KX-TMC97, KX-TMC98		A-3/4	A-3/4	CSTD 24		5
KX-TS5, KX-TS10, KX-TS14, KX-TS15		A-3/4	A-3/4	CSTD 24		5
KX-TS17, KX-TS20, KX-TS21		A-3/4	A-3/4	CSTD 24		5
KX-TS25, KX-TS27, KX-TS50		A-3/4	A-3/4	CSTD 24		5
KX-TS55, KX-TS400, KX-TS500, KX-TS550		A-3/4	A-3/4	CSTD 24		5

Manufacturer Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
Panasonic Continued				Panasonic Continued
KX-TS105, KX-TS108, KX-TS208, TX-TS620	A-3/4	A-3/4	CSTD 24	3,5
KX-TS3282, KX-TS4100, KX-TS4200	A-3/4	A-3/4	CSTD 24	3,5
KX-TS4300, KX-TS4500	A-3/4	A-3/4	CSTD 24	3,5
KX-TSC7-W	A-3/4	A-3/4	CSTD 24	5
KX-TSC14	A-3/4	A-3/4	CSTD 24	3,5
RC-TX91, RC-TX350	A-3/4	A-3/4	CSTD 24	5
RC-TX370, RC-TX420	A-3/4	A-3/4	CSTD 24	5
Fax Phone Series Sets:				
KX-F 50, KX-F 90, KX-F 100, KX-F 130	A-3/4	A-3/4	CSTD 24	5
KX-F 140, KX-F 155, KX-F 230, KX-F 245	A-3/4	A-3/4	CSTD 24	5
KX-F 250, KX-F 500, KX-F 700, KX-F 800	A-3/4	A-3/4	CSTD 24	5
KX-F 3500	A-3/4	A-3/4	CSTD 24	5
SDSB Series Sets:				
VB 42210, VB 42211, VB 42212, VB 42213	A-3/4	A-3/4	CSTD 24	1,5
VA Series Sets:				
VA 61420, VA 61421, VA 61422	A-3/4	A-3/4	CSTD 24	5
VA 61423, VA 8025, VA 8045, VA 8070	A-3/4	A-3/4	CSTD 24	5
VA 8075, VA 8100, VA 8130, VA 8150	A-3/4	A-3/4	CSTD 24	5
VA 8160, VA 8200, VA 8205, VA 8400	A-3/4	A-3/4	CSTD 24	5
VA 8405, VA 8465, VA 9120	A-3/4	A-3/4	CSTD 24	5
<ol style="list-style-type: none"> Headset compatible. Headset compatible. Switch on phone must be set to headset. Has 2.5 mm headset jack. Use the CCEL 190-2 cable. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. For Direct-Connect in the handset jack order the UI 710 for handset use. 				
Phone Mate Corp.				Phone Mate Corp.
3750, 3850, 3950, 3960, 6950	A-3/4	A-3/4	CSTD 01	1
7050, 7150, 7200, 7350, 7650	A-3/4	A-3/4	CSTD 01	1
7850, 8250, 8450, 8750, 8770	A-3/4	A-3/4	CSTD 01	1
9250, 9780, 9870, PAM-2	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Picazo				Picazo
OPS Sets / PCC / CTI-M (TAPI)	A-1/2	A-1/2	CSTD 01	1
VSI DisplayPhone 100, 200	A-1/2	A-1/2	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Plant CML				Plant CML
911 Console	See Note	See Note		1
ElectroKey Panel Mount	See Notes	See Notes		2,3
Maars Desk Console	See Note	See Note		1
Vesta (CTI) Enhanced Herbie: 830808-00302	See Notes	See Notes		2,3
Vesta (CTI) Herbie: 830808-00101	See Notes	See Notes		2,3
Vesta Desk Console	See Notes	See Notes		
<ol style="list-style-type: none"> Consoles with part #'s beginning with: 8509, 8510 or 8511 select one of the following. <ol style="list-style-type: none"> UI 740, position A, transmit 3-4 Direct Connect use the CSTD 01 Consoles with part #'s beginning with: 850306, 850307, 850606, 99918, 99919 or 99920 select one of the following. <ol style="list-style-type: none"> AIA 01 amplifier with the CSTD 01 Cable Direct Connect use the CSHS 01 Cable 				

Manufacturer Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
---	--------------------------------	----------------------------------	---------------------------	------------------------------

Plant CML Continued	Plant CML Continued
<p>2. Some systems may require a 6-wire dual plug prong amplifier. Use the SC911-15A.</p> <p>3. Needs modular to PJ 327 dual plug prong adapter SC-W478. Select one of the following.</p> <p>A. AIA 01 amplifier with the CSTD 01 Cable</p> <p>B. Direct Connect use the CSHS 01 Cable</p>	

Plantronics				Plantronics
Avaya Wireless Headset Telephones: LKA10, 10U100	NO	NO	CCEL 191	
Avaya 8400 One-Touch Adapter: (SOTA) # 65672-01	NO	NO	CSTD 08	
Avaya Partner One-Touch Adapter: # 3276-090	NO	NO	CSTD 08	
A20, S20	NO	NO	CSTD 08	
CA10, CA20, CA40	NO	NO	CCEL 191	
CS10, CT10, CT12	NO	NO	CCEL 191	
CATM10, MX10 (PC Switcher Amplifiers)	NO	NO	CSTD 08	1
DM 15 Amplifier (European) now in the USA	NO	NO	NO	4
E10 "Rep. Not Available" Amplifier	NO	NO	NO	
MHA100 (Mobile Headset Amplifier)	NO	NO	CCEL 190-2	
M10, M12 (Visa Amplifier)	NO	NO	CSTD 08	1
M22 (Visa Amplifier)	NO	NO	CSTD 08	1
P 10, 4-Wire amplifier	NO	NO	NO	2
PLX-400, PLX-500	NO	NO	CSTD 01	
Practica A100	NO	NO	CSTD 01	
S10	NO	NO	CSTD 01	
SHS 2050, 6-Wire "911" amplifier	NO	NO	NO	3
SOH 1858-12 (SP-02)	NO	NO	CSTD 01	
SP-02, SP-04, SP-05	NO	NO	CSTD 01	
SQD Amplifier	NO	NO	NO	
T10, T20 (Single Line Telephones)	NO	NO	CSTD 01	
TBS (Training Base Station)	NO	NO	CSTD 01	
<p>1. Transmit on Amplifier will need to be turned down by one or two notches.</p> <p>2. Plantronics Quick-Disconnect cable is hard wired to the amplifier.</p> <p>3. All Plantronics SHS amplifiers have the Quick-Disconnect cable hard wired to the amplifier.</p> <p>4. Has RJ 45 headset jack. Special wiring using pins 1-4. Unknown formate.</p>				

Polycorn				Polycorn
Soundpoint Pro SE-220, SE-225	A-3/4	A-3/4	CSTD 01	1,3
Soundpoint IP 300, IP400, IP500, IP 600	A-3/4	A-3/4	CSTD 01	4
Soundpoint IP 500	A-3/4	A-3/4	CSTD 01	2
Soundpoint IP 301 SIP, IP 430 SIP	A-3/4	A-3/4	CSTD 01	4
Soundpoint IP 320 SIP, IP 330 SIP	A-3/4	A-3/4	CSTD 01	1,3
Soundpoint IP 501 SIP, IP 601 SIP	A-3/4	A-3/4	CSTD 01	4
Soundpoint IP 310, IP501, IP601, IP650	A-3/4	A-3/4	CSTD 01	4
<p>1. Has 2.5 mm headset jack. Use the CCEL 190-2 cable.</p> <p>2. Connect to dedicated modular headset Jack. Some older IP sets may require the use of CSTD 24 cable instead of the CSTD 01 cable.</p> <p>3. For Direct-Connect in the handset jack order the UI 710 for handset use.</p> <p>4. Connect to dedicated modular headset Jack.</p>				

Positron				Positron
301, 302, 304, 400 Turret	A-8/9	A-8/9	CSHS 01	2,3
600101 Turret	A-8/9	A-8/9	CSHS 01	1,2

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Positron Continued			Positron Continued	
600602, 600211 Turret	A-8/9	A-8/9	CSHS 01	1,2
1. Needs modular to PJ 327 dual plug prong adapter SC-W478. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 3. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Premier Telecom			Premier Telecom	
1A3 Sets	A-3/4	A-3/4	NO	5
2541, 2554, 2572, 2575	A-8/9	A-8/9	NO	3,5
706, 2500, 2530	A-8/9	A-8/9	NO	3,5
Answer Sets : 12, 18, 24, 30	A-3/4	A-3/4	NO	5
DHK Sets	A-8/9	A-8/9	CSHS 01	
ESLI, E-Set	A-3/4	A-3/4	CSTD 01	4
ESP 8, 12, 24	A-3/4	A-3/4	CSTD 01	1,4
Flair II 6, 12, 21, 22, 31, 41	A-3/4	A-3/4	CSTD 01	4
Premier 308, 616, 1648 Keystets	A-8/9	A-8/9	CSHS 01	3,4
Sprint Protegee Sets	A-3/4	A-3/4	CSTD 01	2
1. Headset compatible. 2. Connect to dedicated modular headset Jack. 3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 4. For Direct-Connect in the handset jack order the UI 710 for handset use. 5. Phone sets do not have volume control.				
Prostar Telecom			Prostar Telecom	
Prostar Sets	See Notes	See Notes	See Note	1
1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.				
QTelNet, Inc.			QTelNet, Inc.	
FreeRide VoIP Telephones:				
IP-1301, IP-1302, IP-2301, IP-2302	A-3/4	A-3/4	CSTD 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Radio Shack			Radio Shack	
Dufone Series Sets:				
140, 145, 146, 148, 160, 165, 166, 167	A-3/4	A-3/4	CSTD 01	1
169, 170, 171, 173, 175, 180, 181, 183	A-3/4	A-3/4	CSTD 01	1
185, 188, 192, 195, 196, 202, 203, 204	A-3/4	A-3/4	CSTD 01	1
205, 206, 208, 209, 210, 402, 404, 405	A-3/4	A-3/4	CSTD 01	1
406, 407, 408, 409, 410, 411, 412, 612	A-3/4	A-3/4	CSTD 01	1
ET Series Sets:				
136, 145, 146, 148, 170	A-3/4	A-3/4	CSTD 01	1
175, 180, 181, 189, 190	A-3/4	A-3/4	CSTD 01	1
191, 192, 193, 206, 207	A-3/4	A-3/4	CSTD 01	1
209, 210	A-3/4	A-3/4	CSTD 01	1
ET 3228 Big Button Set	See Note	See Note	See Note	2
System 1752 Telephones	A-3/4	A-3/4	CCEL 190-2	
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.				

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
RCA				RCA
Business Phones:				
25202RE3, 25403RE3, 25404RE3, 25413RE3	NO	NO	CCEL 190-2	
25414RE3, 25415RE3, 25494RE3	NO	NO	CCEL 190-2	
Redcom Laboratories			Redcom Laboratories	
Operator Console	A-8/9	A-8/9	CSHS 01	1,2
Vodas, Vodas-K	A-8/9	A-8/9	CSHS 01	1,2
1. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
2. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Rockwell FirstPoint Contact			Rockwell FirstPoint Contact	
Spectrum Sets:				
SpectraSet 150 Interface box	NO	NO	CSHS 01	1,3
SpectraSet 151 Set	NO	NO	CHS 01	3
SpectraSet (CTI)	NO	NO	CSHS 01	1,3
Spectraview Console (ISDN100)	NO	NO	CSHS 01	1,2,3
Spectraview II Console	NO	NO	CSHS 01	1,2,3
eConnerce Edition VoIP:				
Convergence DeskSet Terminal	NO	NO	CSHS 01	1,3
1. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
2. For Direct-Connect in the handset jack order the UI 710 for handset use.				
3. Sennheiser product applications do not give the "RNA" (Rep. Not Available) feature. The "RNA" feature can only be acquired through headset amplifiers specifically designed with this feature. If this feature is required, check the Setup Guide for the correct Sennheiser interface Cable according to the amplifier used.				
Samsung Telecommunications Systems			Samsung Telecommunications Systems	
DS 24D	A-3/4	NO	CSTD 01	2
DCS Sets:				
7B, Basic 12B, LCD 12B	A-3/4	NO	CSTD 01	1
STD 24B, LCD 24B, LCD C 24	A-3/4	NO	CSTD 01	1
Falcon DCS Sets:				
8 LCD, 18 LCD, 28 LCD Button	A-3/4	NO	CSTD 01	1,2
iDCS Digital Sets 8, 18, 28 Button	A-3/4	NO	CSTD 01	1,2
M-CAT	A-3/4	NO	CSTD 01	2
ProStar Hybrid Sets	A-3/4	NO	CSTD 01	1
ProStar Key Sets	A-3/4	NO	CSTD 01	1
VoIP Key Sets: ITP-5012L, ITP-5021L	A-3/4	NO	CSTD 01	2
1. Headset compatible.				
2. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Sanyo Business Systems			Sanyo Business Systems	
1000, 1100	A-8/9	A-8/9	CSHS 01	1,2
AD Series Sets:				
100, 200, 400, 500	A-3/4	A-3/4	CSTD 01	2
ADX Series Sets:				
160, 260, 360, 460, 660	A-3/4	A-3/4	CSTD 01	2
MD Series Sets:				
3030, 3100, 3300, 3400, 3500	A-3/4	A-3/4	CSTD 01	2
STN Series Sets:				
1000, 1100, 2000, 2100	A-3/4	A-3/4	CSTD 01	2
1. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
2. For Direct-Connect in the handset jack order the UI 710 for handset use.				

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
SBC			SBC	
DKS 830, DKS 925	A-3/4	A-3/4	CSTD 01	3
FA Series Sets:	A-3/4	A-3/4	CSTD 01	3
460, 955, 1200, 1600, 1625, 1900	A-3/4	A-3/4	CSTD 01	3
FC Series Sets:	A-3/4	A-3/4	CSTD 01	3
7, 8, 9, 10, 151, 155, 268	A-3/4	A-3/4	CSTD 01	3
2500, 2505, 2515, 2555	A-3/4	A-3/4	CSTD 01	3
FD Sets: 8000, 8100	A-3/4	A-3/4	CSTD 01	3
FI 125, FH 100	A-3/4	A-3/4	CSTD 01	3
FM Series Sets:	A-3/4	A-3/4	CSTD 01	3
1550, 3500, 3550, 500, 550,	A-3/4	A-3/4	CSTD 01	3
825, 850, 860, 875, 885, 1350	A-3/4	A-3/4	CSTD 01	3
FS 800, FS 900	A-3/4	A-3/4	CSTD 01	3
FT Series Sets:	A-3/4	A-3/4	CSTD 01	3
300, 305, 325, 350, 360, 383	A-3/4	A-3/4	CSTD 01	3
400, 412, 425, 483, 484	A-3/4	A-3/4	CSTD 01	3
SBC 410 Set	A-3/4	A-3/4	CSTD 01	1
SBC a2011-1, a2011-2	A-3/4	A-3/4	CSTD 01	2
<ol style="list-style-type: none"> 1. Connect to dedicated modular headset Jack. 2. Has 3.5 mm (3/8") headset jack. SBC recommends the Tele-Infonet headset adapter cord # CC 300316668 for Universal Amplifiers. Radio Shack also has a adapter P/N 274-397 that the CCEL 190-2 cable can plug into. 3. For Direct-Connect in the handset jack order the UI 710 for handset use. 				
Scitec			Scitec	
Aegis-T, Aegis-T5, Aegis-TP	A-3/4	A-3/4	CSTD 01	2
Aegis-3S, Aegis-5S, Aegis-10S, Aegis-PS	A-3/4	A-3/4	CSTD 01	2
5S-c, STC-7001, STC-7002, STC-7003	A-3/4	A-3/4	CSTD 01	2
HDST-12	A-3/4	A-3/4	CSTD 01	3
IP518	A-3/4	A-3/4	CSTD 01	4
2860C	A-3/4	A-3/4	CSTD 01	2
600T, 600T5, 600TP	A-3/4	A-3/4	CSTD 01	2
6003S, 6005S, 60010S	A-3/4	A-3/4	CSTD 01	2
800T, 800T5, 80003S, 8005S	A-3/4	A-3/4	CSTD 01	2
8128	A-3/4	A-3/4	CSTD 01	2
2510D	A-8/9	A-8/9	CSHS 01	1,2
<ol style="list-style-type: none"> 1. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 2. For Direct-Connect in the handset jack order the UI 710 for handset use. 3. Has 2.5 mm headset jack. Use the CCEL 190-2 cable. 4. Headset compatible. 				
SDX Business Systems			SDX Business Systems	
SPOT Pcphone	See Note	See Note	See Note	1
<ol style="list-style-type: none"> 1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 				
Sharp Electronics			Sharp Electronics	
UX-P100	NO	NO	CSTD 01	
ShoreTel			ShoreTel	
AP 100	A-3/4	A-3/4	CSTD 01	2
AP110	A-3/4	A-3/4	CSTD 01	3

Manufacturer Appliance / Telephone / Terminal			BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
ShoreTel Continued					ShoreTel Continued	
IP 110, IP 210			A-3/4	A-3/4	CSTD 01	2
IP 100, IP 212, IP 230, IP 530, IP 560			A-3/4	A-3/4	CSTD 01	1
SP 100 (SoftPhone)			NO	NO	UUSB 2	
1. Connect to dedicated modular headset Jack. 2. For Direct-Connect in the handset jack order the UI 710 for handset use. 3. Has 2.5 mm headset jack. Use the CCEL 190-2 cable.						
Siemens Communications					Siemens Communications	
Rolm Series Sets:						
120EH, 120H			A-8/9	A-8/9	NO	4,8
240EH, 240H			A-8/9	A-8/9	NO	4,8
400EH, 400H, 400HD2			A-8/9	A-8/9	NO	4,8
Rolm 120 Series Sets:						
61000, 61100, 61300			See Note	See Note		7
Rolm 240 Series Sets:						
62000, 62001, 62080			See Note	See Note		7
62081, 62180, 62181, 62600			See Note	See Note		7
Rolm 400 Series Sets:						
64000, 64001, 64100, 64300, 64500			See Note	See Note		7
312 Series Sets:						
66006, 66007, 66008, 66009			A-3/4	A-3/4	CSTD 01	9
612 Series Sets:						
66106, 66107, 66206, 66207			A-3/4	A-3/4	CSTD 01	1,9
66306, 66307, 66406, 66407			A-3/4	A-3/4	CSTD 01	1,9
624 Series Sets:						
66108, 66109, 66204, 66208			A-3/4	A-3/4	CSTD 01	1,9
66209, 66308, 66309, 66403			A-3/4	A-3/4	CSTD 01	1,9
66404, 66408, 66409			A-3/4	A-3/4	CSTD 01	1,9
9208, 9224			A-3/4	A-3/4	CSTD 01	9
9225			A-8/9	A-8/9	CSHS 01	4,8
9232 Console			A-3/4	A-3/4	CSTD 01	9
9449			See Note	See Note		7
9735, 9755 Console: 51001			A-8/9	A-8/9	CSHS 01	4,8
9765 Console: 90051			A-3/4	A-3/4	NO	5
EKT 34 Button Set			See Note	See Note		7
ETS 100, 200, 300			See Note	See Note		7
Euroset 2100, 2101, 2110			A-3/4	A-3/4	CSTD 01	9
Euroset 2111, 2210, 2212, 2220			A-3/4	A-3/4	CSTD 01	9
Flashphone 2500, 2507			A-8/9	A-8/9	CSHS 01	8,9
GigaSet Series Phones:						
Telephones including Cordless Handset:						
2420, 8825			A-3/4	A-3/4	CSTD 01	6
Cordless Telephones:						
2402, 2410, 2415			NO	NO	CCEL 191	6
4000, 4010, 4015			NO	NO	CCEL 191	6
4200, 4210, 4215			NO	NO	CCEL 191	6
8800, 8825			NO	NO	CCEL 191	6
HCM 12, 16, 24 Button Sets			See Note	See Note		7
HCM 300, 400 Console			See Note	See Note		7
HICOM 9200 Sets			See Note	See Note		7
Memory: 69624			A-3/4	A-3/4	CSTD 24	9

Manufacturer Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
Siemens Continued			Siemens Continued	
S30807, S30817 Console	A-8/9	A-8/9	CSHS 01	8,9
OptiPoint Series Sets: 100, 300	A-3/4	A-3/4	CSTD 24	9
OptiPoint 400 IP Series Sets: 410 Entry Set, 410 Economy Set	A-3/4	A-3/4	CSTD 24	9
410 Standard, 410 Advance, 420 Advance	A-3/4	A-3/4	CSTD 24	10
OptiPoint 500 Digital Series Sets: Entry: 69900	A-3/4	A-3/4	CSTD 24	9
Basic: 69902	A-3/4	A-3/4	CSTD 24	2,9
Standard / SL: 69906, 69907	A-3/4	A-3/4	CSTD 24	2,9
Advance: 69908, 69909	A-3/4	A-3/4	CSTD 24	10
OptiPoint 600: 69983, 69984	A-3/4	A-3/4	CSTD 24	2,9
Optiset "E" Series Phones: Entry: 69660, 69667	A-3/4	A-3/4	CSTD 01	9
Standard: 69662, 69669	A-3/4	A-3/4	CSTD 01	9
Basic: 69661, 69668	A-3/4	A-3/4	CSTD 01	3,9
Advance: 69663, 69670	A-3/4	A-3/4	CSTD 01	3,9
Advance Plus: 69664, 69671	A-3/4	A-3/4	CSTD 01	3,9
Siemens Headset Adapter W/Amplifier: 66967	NO	NO	CSTD 08	
Siemens Trade Board System Console	NO	NO	NO	11
<p>1. If the Siemens Headset Adapter (HRO) #66991 is used select one of the following.</p> <p>A. Active UI setting, A-8/9.</p> <p>B. AIA 01 amplifier with the CSTD 01 Cable</p> <p>C. Direct Connect use the CSHS 24 Cable</p> <p style="padding-left: 40px;">Note: The (HRO) #66991 has both a Modular Jack and Dual Plug Prong Jacks.</p> <p>If the Siemens Headset adapter (EHO) #66957 or #69677 is used select one of the following.</p> <p>A. Active UI setting, A-3/4.</p> <p>B. Direct Connect use the CSTD 01 Cable</p> <p>2. If the Siemens Acoustic Headset Adapter (HRO) #69915 is used select one of the following.</p> <p>A. Active UI setting, A-8/9.</p> <p>B. AIA 01 amplifier with the CSTD 01 Cable</p> <p>C. Direct Connect use the CSHS 24 Cable</p> <p>3. If the Siemens Optiset "E" Headset Plus adapter #69678 is used select one of the following.</p> <p>A. Active UI setting, A-8/9.</p> <p>B. AIA 01 amplifier with the CSTD 01 Cable</p> <p>C. Direct Connect use the CSHS 01 Cable</p> <p>If the Siemens Optiset "E" Headset adapter (EHO) #69677 is used select one of the following.</p> <p>A. Active UI setting, A-3/4.</p> <p>B. Direct Connect use the CSTD 01 Cable</p> <p>4. Needs modular to PJ 327 dual plug prong adapter SC-W478.</p> <p>5. Requires the Rolm part, #9765 ATC Headset Adapter cord. The 9765 cord plugs into the right hand side of the console keyboard. The other end of the 9765 cord plugs into the headset amplifier replacing the 2' coil cord that comes with the Universal Interface. The handset cannot be plugged in when headset is in use.</p> <p>6. Has 2.5 mm headset jack. Use the CCEL 190-2 cable.</p> <p>7. Only compatible with another manufacturers headset amplifier. Check Setup Guide for correct cable.</p> <p>8. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.</p>				

Manufacturer			Manufacturer		
Appliance / Telephone / Terminal		BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Siemens Continued			Siemens Continued		
9. For Direct-Connect in the handset jack order the UI 710 for handset use. 10. Connect to dedicated modular headset Jack. 11. No known standard 6-wire "911" amplifier works on this console.					
Snom Technology			Snom Technology		
190 VoIP, 220 VoIP, 300 VoIP		A-3/4	A-3/4	CSTD 01	1
320 VoIP, 360 VoIP, 370 VoIP		A-3/4	A-3/4	CSTD 01	1
1. Connect to dedicated modular headset Jack.					
Solid State Systems			Solid State Systems		
2B Console		A-8/9	A-8/9	CSHS 01	1,2
2C Console		A-8/9	A-8/9	CSHS 01	1,2
ACD II Agent Set		A-8/9	A-8/9	CSHS 01	1,2
ACD IV: 113-6064, 117-6526		A-3/4	A-3/4	CSTD 01	3
1. Needs modular to PJ 327 dual plug prong adapter SC-W478. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 3. For Direct-Connect in the handset jack order the UI 710 for handset use.					
Solitaire Telecommunications			Solitaire Telecommunications		
ProStar Hybrid Sets		See Note	See Note	See Note	1
ProStar Key Sets		See Note	See Note	See Note	1
Solitaire Plus Five		See Note	See Note	See Note	1
1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.					
Sony			Sony		
AT 500, AT 600, AT 650, AT 850		A-8/9	A-8/9	CSHS 01	1,3
IT-A 205, IT-A 305, IT-A 505		A-8/9	A-8/9	CSHS 01	1,3
IT-A 555, IT-A 4000		A-8/9	A-8/9	CSHS 01	1,3
IT-B 3, IT-B 5		A-8/9	A-8/9	CSHS 01	1,3
IT-D 10, IT-D 20, IT-D 100, IT-D 150		See Note	See Note	See Note	2
IT-D 200, IT-D 250, IT-ID 80		See Note	See Note	See Note	2
IT-K 202, IT-K 300		See Note	See Note	See Note	2
SPP 180, SPP 320		See Note	See Note	See Note	2
1. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 2. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 3. For Direct-Connect in the handset jack order the UI 710 for handset use.					
Sprint Products Group			Sprint Products Group		
Coral FlexSets:					
120, 120D, 120L, 120S		A-3/4	A-3/4	CSTD 01	1,2
280, 280D, 280S		A-3/4	A-3/4	CSTD 01	1,2
PC: 702, 802, 803, 804, 903, 904		A-3/4	A-3/4	CSTD 01	2
Protégé Series Sets		A-3/4	A-3/4	CSTD 01	1,2
SP: 201, 202, 203, 601, 602		A-3/4	A-3/4	CSTD 01	2
Sprint Maestro: 1500 CW, 3500 CW		A-3/4	A-3/4	CSTD 01	2
Sprint Meridian: 9417 CW, 9516 CW		A-3/4	A-3/4	CSTD 01	1,2
1. Headset compatible. 2. For Direct-Connect in the handset jack order the UI 710 for handset use.					

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Startel				Startel
1000, 1200, 1500, 1800	A-8/9	A-8/9	CSHS 01	1,3
2050, 2700, 2800, 3700	A-8/9	A-8/9	CSHS 01	2,3
3710, 3720, 3730	A-8/9	A-8/9	CSHS 01	2,3
1. Needs modular to PJ 327 dual plug prong adapter SC-W478. 2. For Direct-Connect in the handset jack order the UI 710 for handset use. 3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Sun Moon Star Group			Sun Moon Star Group	
Solstar DKTS DK-80	See Note	See Note	See Note	1
Solstar EKTS KT-1011, EKTS KT-48	See Note	See Note	See Note	1
Solstar Feature Phone ST-30	See Note	See Note	See Note	1
1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.				
Tadiran Telecom			Tadiran Telecom	
CCS Series Sets:				
EKT 100, EKT 200, EKT 201	See Note	See Note	See Note	2
EKT 221, EKT 300, EKT 321	See Note	See Note	See Note	2
CCS VDK Digital Set	See Note	See Note	See Note	2
Coral Digital Set DST	A-3/4	A-3/4	CSTD 01	1,3
Coral EKT Display Phone	See Note	See Note	See Note	2
Coral Digital Series Sets:				
DKT 1110, DKT 2100, DKT 2120	A-3/4	A-3/4	CSTD 01	1,3
DKT 2300, DKT 2320, DKT 2321	A-3/4	A-3/4	CSTD 01	1,3
Coral FlexSet Series Sets:				
120, 120D, 280D	A-3/4	A-3/4	CSTD 01	1,3
120S, 280S	A-3/4	A-3/4	CSTD 01	1,3
Emerald Series Sets:				
EKT 8, EKT 16, EKT 24 Button Sets	See Note	See Note	See Note	2
1. Headset compatible. 2. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 3. For Direct-Connect in the handset jack order the UI 710 for handset use.				
TalTek			TalTek	
747VA	See Note	See Note	See Note	1
1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.				
TCO / Alcatel			TCO / Alcatel	
Opus 201, 203, 802, 803	See Note	See Note	See Note	1
Opus VTD 300, CSF 8002	See Note	See Note	See Note	1
1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.				

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Teknekron Infoswitch			Teknekron Infoswitch	
ACD Console 3901	A-8/9	A-8/9	CSHS 01	1,2
ACD Console 3911	A-3/4	A-3/4	CSTD 01	
Data Point Console : 3970	A-8/9	A-8/9	CSHS 01	1,2
Infoswitch 6600, 8600	A-8/9	A-8/9	CSHS 01	2
Orchestra Infoset 931-0294-001	NO	NO	CSTD 01	
1. Needs modular to PJ 327 dual plug prong adapter SC-W478. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Telamon-Tecom			Telamon-Tecom	
T Com, Telamon Set	A-8/9	A-8/9	CSHS 01	1,2
1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Teleco			Teleco	
DKT 1000 SLT	See Note	See Note	See Note	1
EKT 1010 BTS, EKT 1010 SPK	See Note	See Note	See Note	1,2
EKT 1015 BTS, EKT 1015 SPK	See Note	See Note	See Note	1,2
EKT 1020 BLF, EKT 1020 BTS	See Note	See Note	See Note	1,2
EKT 1020 LCD, EKT 1025 BTS	See Note	See Note	See Note	1,2
EKT 1025 LCD	See Note	See Note	See Note	1,2
UST 1010 DHF, UST 1010 DSD	See Note	See Note	See Note	1,3
UST 1020	See Note	See Note	See Note	1,3
1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 2. Has dedicated modular headset Jack. Jack is located behind plastic knockout on the same side as the handset jack. Select one of the following: A. Active UI setting, A-8/9. B. Passive UI setting, A-I with CSHS 01 cable. C. Direct Connect, CSHS 01 with UI 710. 3. If the HHEU or HHEU IIA Headset adapter is used select one of the following: A. Active UI setting, A-8/9. B. Passive UI setting, A-I with CSHS 01. C. Direct Connect, CSHS 01 with UI 710.				
Telecom Technology			Telecom Technology	
ECD Digital Sets, DDS Sets	A-8/9	A-8/9	CSHS 01	1,2
1. Connect to dedicated modular headset Jack. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.				
Telecom USA			Telecom USA	
BCX 5 Button Set: 15008	A-8/9	A-8/9	CSHS 01	2,3
BCX 8 Button Series Sets:				
15110, 15111, 15112, 15113	A-8/9	A-8/9	CSHS 01	2,3
BCX 12 Button Series Sets:				
15210, 15211, 15212, 15213	A-8/9	A-8/9	CSHS 01	2,3
BCX 24 Series Sets:				
15310, 15311, 15312, 15313	A-8/9	A-8/9	CSHS 01	2,3
BCX BLF 8 Button Series Sets:				
15117, 15118, 15517, 15518	A-8/9	A-8/9	CSHS 01	2,3
BCX BLF 12 Button Series Sets:				
15217, 15218, 15617, 15618	A-8/9	A-8/9	CSHS 01	2,3

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Telecom USA Continued			Telecom USA Continued	
BCX BLF 24 Button Series Sets: 15317, 15318, 15717, 15718	A-8/9	A-8/9	CSHS 01	2,3
Challenger Series Sets: 38601, 38602, 38603, 38604	See Note	See Note	See Note	1
ECX Series Sets: 60007, 60010, 60011, 60085, 60086	See Note	See Note	See Note	1
Standard Sets: 616012, 616013	See Note	See Note	See Note	1
<p>1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.</p> <p>2. For Direct-Connect in the handset jack order the UI 710 for handset use.</p> <p>3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.</p>				
TeleConcepts			TeleConcepts	
2500 Premium: 576247	A-8/9	A-8/9	CSHS 01	2,3
2700 MW	See Note	See Note	See Note	1
Capri: 162043, 166043	See Note	See Note	See Note	1
Deluxe Desk: 576148, 576052	See Note	See Note	See Note	1
Feature Phone I: 016067	See Note	See Note	See Note	1
Feature Phone II: 016063	See Note	See Note	See Note	1
Feature Phone III: 026049	See Note	See Note	See Note	1
Feature Phone IV: 016053	See Note	See Note	See Note	1
Feature Phone V: 036212	See Note	See Note	See Note	1
Intercom Phone: 272173	See Note	See Note	See Note	1
Sophisticate: 136043	See Note	See Note	See Note	1
<p>1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.</p> <p>2. For Direct-Connect in the handset jack order the UI 710 for handset use.</p> <p>3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.</p>				
Teleconnect			Teleconnect	
Standard Set: AEKTS-616	A-3/4	A-3/4	CSTD 24	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.				
Teledata Solutions			Teledata Solutions	
Call Link (CTI)	NO	NO	CEDPC 1	
Teledex			Teledex	
Agent MLT-ACD	See Note	See Note	See Note	1
Autocom:				
MLT-A, MLT-B, MLT-C, MLT-1	See Note	See Note	See Note	1
Basic, Basic Plus Sets	See Note	See Note	See Note	1
Business Sets:				
B100	See Note	See Note	See Note	1
B120, B220	A-3/4	A-3/4	CSTD 01	2
B100D, B150D, B250D	A-3/4	A-3/4	CSTD 01	2
BTX 3500, BTX3510	A-3/4	A-3/4	CSTD 01	2
BTX4510, BTX4550, BTX4750	See Note	See Note	See Note	1
Consoles:				
CTX 5, CTX 10, CTX Plus 20	See Note	See Note	See Note	1

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Teledex Continued			Teledex Continued	
Diamond, +3, +5, +10	See Note	See Note	See Note	1
Diamond +L2, +L2-6, +L2A, +L2S, +S	See Note	See Note	See Note	1
Diamond L2E, L2S-5E, L2S-10E,	See Note	See Note	See Note	1
Executive MLT-E	See Note	See Note	See Note	1
SLT-1A, SLT-1B, SLT-2	See Note	See Note	See Note	1
Secretary MLT-S	See Note	See Note	See Note	1
VoIP Network Terminals:				
IP 120D SCCP, IP 250D SCCP	A-3/4	A-3/4	CSTD 01	2
IP 250D SIP	A-3/4	A-3/4	CSTD 01	2
<p>1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.</p> <p>2. Has 2.5 mm headset jack. Use the CCEL 190-2 cable.</p>				
Teledial			Teledial	
Basic Series Sets:				
TDP-1000-7, TDP-1000-10, TDP-1000-12	A-8/9	A-8/9	CSHS 01	2,3
Customer Service Sets:				
TDP-1000-8, TDP-1000-8PB	A-8/9	A-8/9	CSHS 01	2,3
TDP-1000-13, TDP-1000-18, TDP-1000-19	A-8/9	A-8/9	CSHS 01	2,3
Data Sets: TDP-6000-1, TDP-6000-3	A-8/9	A-8/9	CSHS 01	2,3
Dove-Phone: TDP-5000-1	A-8/9	A-8/9	CSHS 01	2,3
Feature Series Sets:				
TDP-1000-1, TDP-1000-1SP	A-8/9	A-8/9	CSHS 01	2,3
TDP-2000-1, TDP-2000-1SP	A-8/9	A-8/9	CSHS 01	2,3
TDP-4000	See Note	See Note	See Note	1
Memory Sets: TDP-100-2, TDP-100-4A	A-8/9	A-8/9	CSHS 01	2,3
Modemphone: TDP-3000-1	A-8/9	A-8/9	CSHS 01	2,3
Restrictor Series Sets:				
TDP-1000-25, TDP-1000-26	A-8/9	A-8/9	CSHS 01	2,3
TDP-1000-3A, TDP-1000-5A	A-8/9	A-8/9	CSHS 01	2,3
TDP-1000-5/6, TDP-1000-6	A-8/9	A-8/9	CSHS 01	2,3
Secured Sets:				
TDP-1000-14, TDP-1000-14FP	A-8/9	A-8/9	CSHS 01	2,3
Triumph Sets	See Note	See Note	See Note	1
<p>1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.</p> <p>2. For Direct-Connect in the handset jack order the UI 710 for handset use.</p> <p>3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.</p>				
Teledirect			Teledirect	
Predictive Dialers: CAT Plus	A-8/9	A-8/9	CSHS 01	1
Predictive Dialers:				
Liberation Version 3, 4, 5	A-8/9	A-8/9	CSHS 01	1
Liberation 6000	A-8/9	A-8/9	CSHS 01	1
<p>1. Compatibility with the use of Teledirect Headset Interface Box # PO-208. Other interface boxes or single line phones can be used. Consult Setup Guide if another manufacturers product is used.</p>				

Manufacturer			Manufacturer		
Appliance / Telephone / Terminal		BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Telephony and Electronics			Telephony and Electronics		
Tynamics Sets: 408, 812, 1024		See Note	See Note	See Note	1
1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.					
Telematrix			Telematrix		
Marquis: 2700, 2702		See Note	See Note	See Note	2
Spectrum Plus Series Sets:					
SP-100		A-3/4	A-3/4	CSTD 01	4
SP-200, SP-300, SP-400		A-3/4	A-3/4	CSTD 01	1
LP-550, SP-550, SP750, SP8312		A-3/4	A-3/4	CSTD 01	1
Spectrum Plus Digital Centrex Phones:					
DC-550, DC-640		A-3/4	A-3/4	CSTD 01	1
TMX Series Sets:					
TMX 25, 100		See Note	See Note	See Note	2
100, 200, 205, 208, 250, 300		A-8/9	A-8/9	CSHS 01	3,5
305, 308, 400, 500, 508, 550		A-8/9	A-8/9	CSHS 01	3,5
TMX Spectrum Series Sets:					
1101, 1102, 1103, 1104, 1105, 2105		A-8/9	A-8/9	CSHS 01	3,5
1. Has dedicated modular headset Jack and 2.5 mm headset jack. Use CCEL 190-2 for the 2.5 mm headset jack.					
2. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.					
3. Connect to dedicated modular headset Jack.					
4. For Direct-Connect in the handset jack order the UI 710 for handset use.					
5. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.					
Teloquent Communications			Teloquent Communications		
Agent Workstation for Windows/NT (CTI)		A-3/4	A-3/4	CSTD 01	1,2
Open@gent for Windows/NT: ISDN (CTI)		A-3/4	A-3/4	CSTD 01	1,2
Open@gent for Windows/NT: POTS (CTI)		A-3/4	A-3/4	CSTD 01	1,2
Teloquent Agent ISDN Telephone (CTI)		A-3/4	A-3/4	CSTD 01	1,2
1. Headset compatible.					
2. For Direct-Connect in the handset jack order the UI 710 for handset use.					
Telrad			Telrad		
Avanti Series Sets:					
3000, 3015DF, 3015DH		See Note	See Note	See Note	1
3020F, 3020H, 3025		See Note	See Note	See Note	1
BX DisplayPhone Sets:					
83050-0000, 83050-0100		See Note	See Note	See Note	1
Headset Station DisplayPhone:					
73430-0000, 73430-0001		See Note	See Note	See Note	1
Digital BX Series Sets:					
BA1, BA2, EX1, EX2		See Note	See Note	See Note	1
SB3, SD1, SD2, SD60		See Note	See Note	See Note	1
Symphony Console: 73-00-1000		A-8/9	A-8/9	CSHS 01	2,3
Symphony Console: 73-00-2000		A-8/9	A-8/9	CSHS 01	2,3
Symphony Sets : 20, 24, 32 Button		See Note	See Note	See Note	1

Manufacturer			Manufacturer		
Appliance / Telephone / Terminal		BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Telrad Continued			Telrad Continued		
<p>1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturer's amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.</p> <p>2. For Direct-Connect in the handset jack order the UI 710 for handset use.</p> <p>3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.</p>					
TelStrat			TelStrat		
i2732 IP Telephone		C-3/4	C-3/4	CSTD 08	1
1. Connect to dedicated modular headset Jack.					
Teltone			Teltone		
T-311 Telephone Access Unit		A-3/4	A-3/4	CSTD 24	1
1. Connect to dedicated modular headset Jack.					
Teltronics			Teltronics		
Cypreon Series Sets:					
CIP10, CIP17, CIP200, CIP210		A-5	A-5	CHS 24	1,2
SRX 911 Set, 9700 Set		A-8/9	A-8/9	CSHS 01	1,2
SRX Vision Phones:					
100, 200, 400, 1000,		A-8/9	A-8/9	CSHS 01	1
1. For Direct-Connect in the handset jack order the UI 710 for handset use.					
2. The AIA 01 In-Line Amplifier can also be used with the CSTD 01 cable.					
TIE Communications			TIE Communications		
Bus Com Series Sets:					
15008, 15013, 15017, 15105, 15110		A-8/9	A-8/9	CSHS 01	1
15111, 15112, 15113, 15210, 15117		A-8/9	A-8/9	CSHS 01	1
15118, 15211, 15212, 15213, 15217		A-8/9	A-8/9	CSHS 01	1
15218, 15310, 15311, 15312, 15313		A-8/9	A-8/9	CSHS 01	1
15317, 15318, 15517, 15518, 15617		A-8/9	A-8/9	CSHS 01	1
15618, 15717, 15718		A-8/9	A-8/9	CSHS 01	1
Bus Com III & IV Series Sets					
Bus Com: TC8, TC8DS, TC12, TC22		A-8/9	A-8/9	CSHS 01	1
Business Com Series Sets:					
60010, 60011, 60012, 60085, 60086		A-3/4	A-3/4	CSTD 01	1
Command CBX 816: 83011		A-8/9	A-8/9	CSHS 01	1
Custom Calling Set: 71325		A-3/4	A-3/4	CSTD 01	1
Data Key Series Sets:					
88176, 88254, 89758, 89759, 89760		A-3/4	A-3/4	CSTD 01	1
89761, 89762, 89763, 89764, 89765		A-3/4	A-3/4	CSTD 01	1
Data Link: T5030		See Note	See Note	See Note	2
DCX Series Sets:					
88176, 88254, 89758, 89759, 89760		A-3/4	A-3/4	CSTD 01	1
89761, 89762, 89763, 89764, 89765		A-3/4	A-3/4	CSTD 01	1
Delphi Series Sets:					
60030, 60031, 60080, 60081, 86057		A-3/4	A-3/4	CSTD 01	1
86063, 86067, 86072, 87730, 87731		A-3/4	A-3/4	CSTD 01	1
87732, 87733		A-3/4	A-3/4	CSTD 01	1
Delphi 4: EK 416		A-8/9	A-8/9	CSHS 01	1
Delphi Data Star Series Sets:					
88161, 88163, 89750, 89760, 89761		A-3/4	A-3/4	CSTD 01	1
89763, 89764		A-3/4	A-3/4	CSTD 01	1

Manufacturer Appliance / Telephone / Terminal			BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Manufacturer Notes
TIE Communications Continued			TIE Communications Continued			
DSO 1 Series Sets:						
88661, 88662, 88663			A-3/4	A-3/4	CSTD 01	
E200-AR, -AT, -BR, -BT			A-8/9	A-8/9	CSHS 01	1
E201-AR, -AT, -BR, -BT			A-8/9	A-8/9	CSHS 01	1
Econokey 1A2E: 60025, 60026			A-3/4	A-3/4	CSTD 01	
EK Series Sets:						
86073, 86074, 86078, 86079			A-3/4	A-3/4	CSTD 01	
86082, 86088, 86089			A-3/4	A-3/4	CSTD 01	
Meritor Series Sets:						
86057, 86063, 86067, 86072, 87730			A-3/4	A-3/4	CSTD 01	
87731, 87732, 87733			A-3/4	A-3/4	CSTD 01	
Mod Key Series Sets:						
60007, 60082, 60084			A-3/4	A-3/4	CSTD 01	
Onyx Series Sets:						
88154, 88155, 88160, 88163			A-3/4	A-3/4	CSTD 01	
88250, 88260, 88261, 88263			A-3/4	A-3/4	CSTD 01	
88350, 88361, 88363			A-3/4	A-3/4	CSTD 01	
Paragon Series Sets:						
EK616, 61650, 61655			See Note	See Note	See Note	2
TCX Series Sets:						
86050, 86060, 86061, 86070			A-8/9	A-8/9	CSHS 01	1
86071, 86080, 86098			A-8/9	A-8/9	CSHS 01	1
Turret Series Consoles:						
T1030-2, T1030-3, T1060-2, T1060-3			A-8/9	A-8/9	CSHS 01	1
T1060-4, T1220-2, T1220-3, T1220-4			A-8/9	A-8/9	CSHS 01	1
Ultracom Series Sets:						
86057, 86063, 86067, 86072			A-3/4	A-3/4	CSTD 01	
87730, 87731, 87732, 87733			A-3/4	A-3/4	CSTD 01	
Ultracom AT (UAT) Series Sets:						
10816, 10817, 10832, 10864, 10868			A-8/9	A-8/9	CSHS 01	1
Ultrakey: 60015, 60016			A-3/4	A-3/4	CSTD 01	
VDS Series Sets:						
89050, 89053, 89054			A-3/4	A-3/4	CSTD 01	
89055, 89060, 89061			A-3/4	A-3/4	CSTD 01	
<p>1. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.</p> <p>2. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturer's amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use.</p>						
Tone Commander Systems			Tone Commander Systems			
CentraCom: 30E, ES120, 200			A-8/9	A-8/9	CSHS 01	2,5,6
CentraCom: CTX 10 Plus, 20 Plus			A-8/9	A-8/9	CSHS 01	2,5,6
Innovator II Console: CTX-5, 10, 20			A-8/9	A-8/9	CSHS 01	1,6
ISDN: 522, 524, 532, 1030, 1560, 2260d			A-8/9	A-8/9	CSHS 01	1,6
ISDN: 30e120, 40d120, 40d240 Consoles			A-8/9	A-8/9	CSHS 01	1,6
ISDN 6210, 6220, 6230			A-3/4	A-3/4	CSTD 24	3,5
ISDN 6220T-TSG Secure Telephone			NO	NO	NO	4
ISDN 8610, 8620			A-3/4	A-3/4	CSTD 01	7
ISDN 8810			A-3/4	A-3/4	CSTD 01	7

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Tone Commander Continued			Tone Commander Continued	
VoIP 7210, 7220, 7310, 7320	A-3/4	A-3/4	CSTD 24	3,5
VoIP 7610, 7620	A-3/4	A-3/4	CSTD 01	3,5
VoIP 7810	A-3/4	A-3/4	CSTD 01	7
1. Needs modular to PJ 327 dual plug prong adapter SC-W478. 2. The console may have Dual Plug Prong Jacks, if it does, refer to Note 1. 3. Headset compatible. 4. Headset use not recommended with TSG-Secure ISDN Telephone. 5. For Direct-Connect in the handset jack order the UI 710 for handset use. 6. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 7. Connect to dedicated modular headset Jack.				
Toshiba Telecommunications			Toshiba Telecommunications	
Add on 20 button Line Module for Toshiba Sets:				
DADM 3020, DADM 3120	NO	NO	NO	
CIX IP Telephones:				
IPT 2008, IPT 2010-SD, IPT 2020-SD	A-3/4	A-3/4	CSTD 01	2,5
Console: CTX Attendant	A-3/4	A-3/4	CSTD 01	8
Console: DATT102, 8245G9	A-8/9	A-8/9	CSHS 01	5,6
Console: MDSS302	A-8/9	A-8/9	CSHS 01	5,6
Console: Perception 4000	A-8/9	A-8/9	CSHS 01	1,6
Console: Strata Attendant	A-8/9	A-8/9	CSHS 01	4,6
D4000 ACD Console	A-3/4	A-3/4	CSTD 01	2,5
DKE 2000 Series Sets	A-3/4	A-3/4	CSTD 01	2,5
DKE 3000 Series Sets	A-3/4	A-3/4	CSTD 01	2,5
DKT 2000 Series Sets:				
DKT 2010, DKT 2020	A-3/4	A-3/4	CSTD 01	2,5
DKT 3000 Series Sets:				
DKT 3001	See Note	See Note	See Note	7
DKT 3010S, DKT 3010SD, DKT 3014SD	See Note	See Note	See Note	2,7
DKT 3020S, DKT 3020SD	See Note	See Note	See Note	2,7
DKT 3210 DKT 3220	See Note	See Note	See Note	2,7
EKT 1020, EKT 6500	A-3/4	A-3/4	CSTD 01	2,5
EKT 6510, EKT 6515	A-3/4	A-3/4	CSTD 01	2,5
EKT 6520, EKT 7510	A-3/4	A-3/4	CSTD 01	2,5
Fax Phone 4700	See Note	See Note	See Note	7
Perception: DKT 1010, 1020 SD	A-3/4	A-3/4	CSTD 01	2,5
Strata "E" Series Sets:				
EKT 6000N	See Note	See Note	See Note	7
EKT 6010, 6015, 6020, 6025	See Note	See Note	See Note	3,7
Strata "S" Series Sets:				
MKSU 202, MKSU 502	A-8/9	A-8/9	CSHS 01	5,6
TSX-14, TSX-16, TSX-18	A-8/9	A-8/9	CSHS 01	5,6
Strata III: EKT-102, EKT-103	A-8/9	A-8/9	CSHS 01	5,6
Strata VI, XII, XX Series Sets:				
EKT 2101, EKT 2102, EKT 2103	See Note	See Note	See Note	2,7
EKT 2104, EKT 2105, EKT 2106	See Note	See Note	See Note	2,7
EKT 2201, EKT 2202, EKT 2203	See Note	See Note	See Note	2,7
EKT 2204, EKT 2205	See Note	See Note	See Note	2,7
EKT 3101, EKT 3102	See Note	See Note	See Note	2,7
Toshiba Com	See Note	See Note	See Note	2,7

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Toshiba Continued			Toshiba Continued	
<ol style="list-style-type: none"> 1. Plug headset amplifier into headset jack on the left side of the console. 2. If the Toshiba BHEU, HHEU or HHEU IIA Headset adapter is used, select one of the following: <ol style="list-style-type: none"> A. Active UI setting, A-8/9. B. Direct Connect, CSHS 01 with UI 710. 3. Has dedicated modular headset Jack. Jack is located behind plastic knockout on the same side as the handset jack. Select one of the following: <ol style="list-style-type: none"> A. Active UI setting, A-8/9. B. Direct Connect, CSHS 01 with UI 710. 4. Needs modular to PJ 327 dual plug prong adapter SC-W478. 5. For Direct-Connect in the handset jack order the UI 710 for handset use. 6. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 7. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones using the handset jack. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 8. Headset compatible. 				
TT Systems			TT Systems	
Altair: I, II, III	See Note	See Note	See Note	1
Regal: I, II	See Note	See Note	See Note	1
SimTel: II, III, IV, V	See Note	See Note	See Note	1
SimTel Series Sets:				
100, 200, 205, 208, 210, 410, 412	See Note	See Note	See Note	1
4012, 4300, 5200-TT, 5300-BLF	See Note	See Note	See Note	1
TT-80 PCW, TT-112 P	See Note	See Note	See Note	1
<ol style="list-style-type: none"> 1. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 				
Turret Equipment Corp.			Turret Equipment Corp	
3000 Turret	A-8/9	A-8/9	CSHS 01	1,2
<ol style="list-style-type: none"> 1. For Direct-Connect in the handset jack order the UI 710 for handset use. 3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 				
Uniden			Uniden	
410, 420	A-3/4	A-3/4	CSTD 01	1
1010, 1015, 1020	A-8/9	A-8/9	CSHS 01	
1030, 1040, 8050	A-8/9	A-8/9	CSHS 01	
1050	See Note	See Note	See Note	2
XE20, XE30, XE40, XE70	A-8/9	A-8/9	CSHS 01	
Wireless Business Phones VoIP 900 MHz:				
ANA9310, ANA9320, ANA9710	NO	NO	CCEL 190-2	
Digital Cordless Phones 5.8 GHz:				
CLX465, CLX485	NO	NO	CCEL 190-2	
Digital Cordless Phones 2.4 GHz:				
DCT646, DCT646-2, DCT648, DCT648-2	NO	NO	CCEL 190-2	
DCT746M, DCT746-2, DCT748-2	NO	NO	CCEL 190-2	
DCT748-3, DCT6465, DCT6465-2	NO	NO	CCEL 190-2	
DCT6485, DCT6485-2, DCT7488-2	NO	NO	CCEL 190-2	
DCX640, DCX700, DCX770	NO	NO	CCEL 190-2	
DMX776, DMX778	NO	NO	CCEL 190-2	

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Uniden Continued			Uniden Continued	
Digital Cordless 900 MHz: EXI8966	NO	NO	CCEL 190-2	
Digital Cordless Phones 5.8 GHz:				
ELBT585, ELBT595, ELT560, ELX500	NO	NO	CCEL 190-2	
TCX400, CTX440, TCX800, TCX860	NO	NO	CCEL 190-2	
TRU8860, TRU8860-2, TRU8865	NO	NO	CCEL 190-2	
TRU8865-2, TRU8866, TRU8880-2	NO	NO	CCEL 190-2	
TRU8885, TRU8885-2, TRU8888	NO	NO	CCEL 190-2	
Business Phones VoIP:				
UIP200, UIP300, UIP312, UIP1868	NO	NO	CCEL 190-2	
<ol style="list-style-type: none"> 1. Connect to dedicated modular headset Jack. 2. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 				
USB Recorder			USB Recorder	
Sparky + (2-way phone recorder for PC)	NO	NO	CCEL 190-2	1
1. Has 2.5 mm headset jack.				
USX Telecenters			USX Telecenters	
1010-BTS, 1010-SPK, 1010-BLS	A-8/9	A-8/9	CSHS 01	1,4
1020-BTS, 1020-SPK, 1020-LCD	A-8/9	A-8/9	CSHS 01	1,4
Console: 1240, 1250	A-8/9	A-8/9	CSHS 01	3,4
EKT-O-Button	See Note	See Note	See Note	2
<ol style="list-style-type: none"> 1. Connect to dedicated modular headset Jack. 2. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. 3. For Direct-Connect in the handset jack order the UI 710 for handset use. 4. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 				
V-Band Systems			V-Band Systems	
Valent 10, 20, 30	A-3/4	A-3/4	CSTD 01	1
Viax 60 Console : PL56001	A-3/4	A-3/4	CSTD 01	1
Viax Desk Phone, Console	A-3/4	A-3/4	CSTD 01	1
Viax Tomcat	A-8/9	A-8/9	CSHS 01	1,2
VK-6000 to 6150 Turret	A-8/9	A-8/9	CSHS 01	1,2
VK-7030 to VK-70240	A-3/4	A-3/4	CSTD 01	1
<ol style="list-style-type: none"> 1. For Direct-Connect in the handset jack order the UI 710 for handset use. 2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 				
Vertical Networks			Vertical Networks	
InstantOffice VoIP Telephony:				
Digital Sets: 8, 16, 32 Button Sets	A-3/4	A-3/4	CSTD 01	1,2
<ol style="list-style-type: none"> 1. Headset compatible. 2. For Direct-Connect in the handset jack order the UI 710 for handset use. 				
VCON			VCON	
Desktop Videoconferencing:				
Cruiser 75, Cruiser 85, Escort 25	NO	NO	CSTD 01	
Cruiser 384 Series	NO	NO	CEDPC 1	
ViGo Series, Vpoint	NO	NO	CEDPC 1	
Vodavi Communications			Vodavi Communications	
Starplus Proprietary Sets:				
612, 1648, 3264	A-8/9	A-8/9	CSHS 01	4,5

Manufacturer			Manufacturer	
Appliance / Telephone / Terminal	BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
Vodavi Continued			Vodavi Continued	
Starplus Series Sets:				
2500, 2554, 4500	A-8/9	A-8/9	CSHS 01	4,5
2701, 2702, 2703	See Note	See Note	See Note	2
2704, 2705, 2706	See Note	See Note	See Note	2
2801, 2802, 2803	NO	NO	CSTD 01	4
Starplus II Series Sets:				
2601, 2602, 2603, 2604, 2605	See Note	See Note	See Note	2
2606, 2631, 2635, 2636	See Note	See Note	See Note	2
Starplus DHS 7312, 7314	A-3/4	A-3/4	CSTD 24	3,4
Starplus Digital Series Sets:				
Basic, Enhanced, Executive	A-3/4	A-3/4	CSTD 24	1,4
Starplus EX Series Sets:				
EX Basic, EX Enhanced, EX Executive	A-3/4	A-3/4	CSTD 24	1,4
Starplus STS 3515-71	A-3/4	A-3/4	CSTD 24	1,4
Starplus STS Wanderer 9018-75 Cordless	See Note	See Note	See Note	1
Infinite Series Sets:				
3011, 3012, 3015, 3016, 3017	A-3/4	A-3/4	CSTD 24	1,4
Infinite Series Sets, Second Generation:				
IN 9011, IN 9012, IN 9013	A-3/4	A-3/4	CSTD 24	3,4
IN 9014, IN 9015, IN 9016	A-3/4	A-3/4	CSTD 24	
DVX Basic, DVX Enhanced, DVX Executive	A-3/4	A-3/4	CSTD 24	1,4
Telenium IP Series Sets:				
3810-00, 3813-01, 3813-02	A-3/4	A-3/4	CSTD 24	3,4
Triad S, XTS, XTSC Series Sets:				
TR 9011, TR-9013, TR-9014	A-3/4	A-3/4	CSTD 24	3,4
TR-9015, TR 9016	A-3/4	A-3/4	CSTD 24	3,4
<ol style="list-style-type: none"> Has 2.5 mm headset jack. Use the CCEL 190-2 cable. Sennheiser Amplifiers and Direct-Connect Cables are not compatible with these phones. If the phone has another manufacturers amplifier connected to it Sennheiser will most likely have a connecting Cable for that amplifier. Check the Setup Guide for manufacturer's amplifier model in use. Headset compatible. For Direct-Connect in the handset jack order the UI 710 for handset use. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used. 				
VTech			VTech	
Wireless Phones:				
2406, 2418, 2426, 2434	NO	NO	CCEL 190-2	
2451, 2456, 2498	NO	NO	CCEL 190-2	
2528, 2551, 2558	NO	NO	CCEL 190-2	
2600, 2625, 2650, 2651, 2656	NO	NO	CCEL 190-2	
5801, 5803, 5807, 5820, 5825, 5831	NO	NO	CCEL 190-2	
5850, 5853, 5857, 5866, 5867, 5881	NO	NO	CCEL 190-2	
9127, 9152, 9162	NO	NO	CCEL 190-2	
20-2420, 20-2431, 20-2481	NO	NO	CCEL 190-2	
40-2420, 40-2421	NO	NO	CCEL 190-2	
VXI			VXI	
TuffSet CT Switch, TuffSet Everon	NO	NO	CSTD 24	
TuffSet Carbon	NO	NO	CSTD 01	
VXI Dialpad 201211 (headset phone)	NO	NO	CSTD 01	

Manufacturer		Manufacturer			
Appliance / Telephone / Terminal		BW 900 Bluetooth Headset	UI 740, 750 & 760 Settings	Direct-Connect Cable #	Notes
WIN Communications		WIN Communications			
WIN Digital Multiline Telephones:					
20 Button Basic	A-3/4	A-3/4	CSTD 24	1,2	
20 Button Display, 32 Button Display,	A-3/4	A-3/4	CSTD 24	1,2	
20 Button Non-Display, 32 Button Non-Display	A-3/4	A-3/4	CSTD 24	1,2	
DSS / BLF Console	A-3/4	A-3/4	CSTD 24	2	
DX Series Sets:					
Basic Digital, Standard Digital,	A-3/4	A-3/4	CSTD 24	1,2	
Digital Display, Enhanced Digital	A-3/4	A-3/4	CSTD 24	1,2	
Executive Digital	A-3/4	A-3/4	CSTD 01	1,2	
Marathon DKT	A-3/4	A-3/4	CSTD 24	2	
MK 440 CT	A-8/9	A-8/9	CSHS 01	2,3	
Poets Series Sets:					
118, 612, 1836, 3060	A-3/4	A-3/4	CSTD 24	2	
Reliant Series Sets:					
8, 16, 32, 50, 96	A-8/9	A-8/9	CSHS 01	2,3	
1. Headset compatible.					
2. For Direct-Connect in the handset jack order the UI 710 for handset use.					
3. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.					
Xinex Networks		Xinex Networks			
mindSet: mS 1201	A-3/4	A-3/4	CSTD 01	2	
mindSet: mS 1202	A-3/4	A-3/4	CSTD 01	1,2	
1. Headset compatible.					
2. For Direct-Connect in the handset jack order the UI 710 for handset use.					
Zetron		Zetron			
Desktop Series Consoles:					
7D+, 94, 230A, 260, 280, 284	A-8/9	A-8/9	CSHS 01	1,2	
Z370, 4014, 4016, 4018, 4217	A-8/9	A-8/9	CSHS 01	1,2,3	
Integrator RD Console 4217 NT	A-8/9	A-8/9	CSHS 01	1,2	
Rackmount Series Consoles:					
4010, 4010R, 4115, 4116, 4117, 4118	A-8/9	A-8/9	CSHS 01	1,2,3	
TETRA Wireless Console DCS-5020	A-8/9	A-8/9	CSHS 01	1,2	
Turret: 3100, 3130	A-8/9	A-8/9	CSHS 01	1,2	
1. For Direct-Connect in the handset jack order the UI 710 for handset use.					
2. The AIA 01 In-Line Amplifier with CSTD 01 cable can also be used.					
3. Some Consoles may require a 6-wire dual plug prong amplifier. Use the SC911-15A.					
Zultys Technologies		Zultys Technologies			
LIPZ4 (SIP Soft Phone)	A-3/4	A-3/4	CSTD 01	4	
WIP 2 (Wi-Fi)	NO	NO	UUSB 2		
ZIP 2, ZIP 2+, ZIP 2P, ZIP 2X2, ZIP 2X2L	A-3/4	A-3/4	CSTD 01	1	
ZIP 4X4	A-3/4	A-3/4	CSTD 01	1,2	
ZIP 4X5	A-3/4	A-3/4	CSTD 01	1,2,3	
1. For Direct-Connect in the handset jack order the UI 710 for handset use.					
2. Has 2.5 mm headset jack. Use the CCEL 190-2 cable.					
3. Bluetooth enabled for use with wireless Bluetooth headset.					
4. Headset compatible.					

Warranty Conditions

Sennheiser Communications USA

The guarantee period for Sennheiser products is 24 months from the date of purchase. Sennheiser accessories are warranted for 60 days. Excluded are rechargeable or disposable batteries that are delivered with the product; due to their characteristics these products have a shorter service life that is principally dependent on the individual frequency of use.

The guarantee period starts from the date of original purchase. For this reason, we recommend that the sales receipt be retained as proof of purchase. Without this proof (which is checked by the responsible Sennheiser service partner) you will not be reimbursed for any repairs that are carried out.

Depending on our choice, guarantee service comprises, free of charge, the removal of material and manufacturing defects through repair or replacement of either individual parts or the entire device. Inappropriate usage (e.g. operating faults, mechanical damages, incorrect operating voltage), wear and tear, excessive force and defects which were known at the time of purchase are excluded from guarantee claims. The guarantee is void if the product is manipulated by non-authorized persons or repair stations.

In the case of a claim under the terms of this guarantee, send the device, including accessories and sales receipt, to the responsible service partner. To minimize the risk of transport damage, we recommend that the original packaging is used. Your legal rights against the seller, resulting from the contract of sale, are not affected by this guarantee.



RETURN MATERIAL AUTHORIZATION (RMA)

Please select **one** of the following options for repair or replacement:

- 1.) Create a Service Request on our website: <http://sennheiserusa.com>. Click on the service tab and follow instructions.
- 2.) Fax this form, once completed, to 1-860-434-0827 for an advanced replacement shipped within 72 hours of receipt. Put a copy of this form in the box. **Advance replacement requires a valid credit card number.**
- 3.) Call our Service Department at 1-877-736-6434 then press 3, and then press option 1 from 8 AM – 8 PM EST to obtain RMA # to return equipment.
- 4.) Complete this form and enclose it in your package. We will assign RMA # when we receive the product.

For current “Out of Warranty” repair pricing, call our Service Department at 1-877-736-6434 then press 3, and then press option 1 from 8 AM – 8 PM EST.

Sennheiser Communications
Attn: Service Department
One Enterprise Drive
Old Lyme, CT 06371

Ship-to Information:

Contact Name: _____

Company: _____

Address: _____

City: _____ State: _____ Zip: _____ Phone#: _____

Credit Card #: _____ Exp.Date: (MM/YYYY) _____

Name as it appears on the Credit Card: _____

Model Number	Alphanumeric Code*	Quantity

*The plastic band on the headsets and accessory cords contain a series of four letter followed by three alphanumeric codes, example: ZTZV A05. This must be recorded.

Dealer that you purchased the product from: _____